

Leading and Trailing Edge Bell-Press LED Dimmer Summary of Settings

- **2 x bell-presses**
Turn lamp on to 50% intensity, irrespective of previous state – mostly for use with Shuttle Master Zone Controller (MZC)
- **5 x bell-presses** (setting available for Trailing Edge only *1)
Auto setting for the Osram PAR16 50 Advanced 5.3W LED
(500W and 800W dimmers: first implementation March 2015)
(125W dimmer: to be implemented Sept 2015)
- **9 x bell-presses** (*1)
Set the minimum dim level to lower than factory default
- **11 x bell-presses** (*2)
Set the minimum dim level to a user selected level
- **13 x bell-presses** (*1)
Reset all settings to factory default
- **15 x bell-presses** (setting available for Trailing Edge only *1)
Compatibility mode for certain electronic transformer/LED combinations
- **17 x bell-presses** (setting available for Trailing Edge only *3)
Set the maximum dim level to a user selected level

(*1) *Tip – first dim to a low intensity. If the dimmer accepts the setting, the lamps will go to full intensity.*

(*2) *If the dimmer accepts the setting, the lamps will go to full intensity*

(*3) *If the dimmer accepts the setting, the lamps will go to minimum intensity*