

SHUTTLE DIMMERS LAMP COMPATIBILITY & MAXIMUM LAMP LOADS – Version: JULY 2024

Shuttle 1.8kVA Rotary 1-10V Dimmer (SDIMR-1-10V-1800VA)

| LAMP/DRIVER BRAND | LAMP/DRIVER MODEL and WATTAGE | DRIVER | DIMMING MODE | MAXIMUM NUMBER OF LAMPS/FITTINGS | |
|---|--|----------------------|--------------|----------------------------------|----------------|
| | | | | 1 – 10V Control Port | Mains Switch |
| Any Brand | Any 1-10V (or 3-in-1 dim compatible) Model and Wattage | Internal or External | 1-10V | 1 – 100 | 1800VA (8 Amp) |
| Use an external contactor wired via the 1-10V dimmer's mains switch for loads in excess of 1.8kVA or when exceeding the integrated non-replaceable fuse's 370 A ² s rating | | | | | |

Shuttle 96W Bell-Press DC Dimmer (DC-LED-96W)

| LAMP BRAND | DRIVER MODEL and WATTAGE | DRIVER | DIMMING MODE | MAXIMUM LOAD |
|---|--|----------------------|--------------|------------------------------|
| | | | | 12-48V DC operation |
| Any 12-48V LED Strip | Any 12VDC, 24VDC or 48VDC constant voltage PSU | Internal or External | PWM | 96W (12V/8A, 24V/4A, 48V/2A) |
| Compatible with other low voltage lamps that are PWM dimmable. Power supply must be IEC 61347 compliant | | | | |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|----|---------------|---------------------------------|------|----------|-------------------------------|-------------------------|--------|--------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 1 | ACDC Dynamics | TP-DC-10W E27 | 10.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 38 |
| 2 | ACDC Dynamics | DIM-R68-8W-CW E27 | 8.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 65 | 1 - 115 |
| 3 | ACDC Dynamics | DIM-R68-8W-WW E27 | 8.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 65 | 1 - 115 |
| 4 | ACDC Dynamics | DIM-A60-S10W-E27-CW | 10.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 5 | ACDC Dynamics | BF-T45-S E27 Filament | 2.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 48 | 1 - 86 |
| 6 | ACDC Dynamics | GL-P12WA-CW Panel Light | 12.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 7 | ACDC Dynamics | DIM-R50-6W-CW | 6.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 8 | ACDC Dynamics | AS-C35-ST E14 Filament | 2.0 | Internal | Trailing Edge | 1 - 28 | 1 - 48 | 1 - 53 | 1 - 103 | 1 - 182 |
| 9 | ACDC Dynamics | BF-C35-Q Filament Lamp (candle) | 2.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|----|----------------|------------------------------|------|--------------------|-------------------------------|-------------------------|--------|--------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 10 | ACDC Dynamics | BF-C35-Q Decor Lamp (candle) | 2.0 | Internal | Trailing Edge | 1 - 23 | 1 - 40 | 1 - 44 | 1 - 85 | 1 - 151 |
| 11 | ACDC Dynamics | LEDA35E-WW | 4.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 65 |
| 12 | ACDC Dynamics | DIM-MS-GU10-5W-CW | 5.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 65 | 1 - 115 |
| 13 | ACDC Dynamics | DIM-KL-GU10-7W-CW | 7.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 90 |
| 14 | ACDC Dynamics | LCM8106-60DIM-WW PAR38 | 18.0 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 31 |
| 15 | ACDC Dynamics | LCM8106-60DIM-CW PAR38 | 18.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 13 | 1 - 23 |
| 16 | ACDC Dynamics | DIM-PAR30-12W-CW | 12.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 11 | 1 - 20 |
| 17 | ACDC Dynamics | LCM8106-160DIM-CW PAR38 | 18.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 13 | 1 - 23 |
| 18 | ACDC Dynamics | DIM-PAR20-10W-CW | 10.0 | Internal | Trailing Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 16 | 1 - 29 |
| 19 | ACDC Dynamics | LEDC35E-E27-CW Candle | 3.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 20 | ACDC Dynamics | LEDC35E-E27 (Candle) | 3.5 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 55 | 1 - 98 |
| 21 | ACDC Dynamics | LEDC212-CW | 3.0 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 22 | ACDC Dynamics | DIM-GU10-35-60-CW | 4.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 55 |
| 23 | ACDC Dynamics | DIM-GU10-5W-CW (1x sample) | 5.0 | Internal | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 9 | 1 - 17 |
| 24 | ACDC Dynamics | DIM-KL-MR16-7W-CW | 7.0 | External (LW70) | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 25 | ACDC Dynamics | DIM-MR16-GW-CW | 4.0 | External (LW70) | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 65 | 1 - 115 |
| 26 | ACDC Dynamics | DIM-MR16-35-60-DL | 4.0 | External (LW70) | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 27 | ACDC Dynamics | DIM-MR16-35-60-CW | 4.0 | External (LW70) | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 28 | ACDC Dynamics | DIM-MR16-35-60-CW-230 | 4.0 | External (LW70) | Trailing Edge | 1 - 35 | 1 - 60 | 1 - 67 | 1 - 130 | 1 - 231 |
| 29 | ACDC Dynamics | DIM-GU10-5W-DL-5Y | 5.0 | Internal | Trailing Edge | 2 - 13 | 2 - 23 | 2 - 25 | 2 - 48 | 2 - 86 |
| 30 | ACDC Dynamics | TP-DL-10W E27 | 10.0 | Internal | Leading Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 10 | 1 - 18 |
| 31 | ACDC Dynamics | G9 Lamp DIM-G9-3W-CW/2 | 3.0 | Internal | Trailing Edge | 1 - 27 | 1 - 47 | 1 - 52 | 1 - 102 | 1 - 181 |
| 32 | ACDC Dynamics | Candle Lamp LEDC35L-E14-CW | 5.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 63 | 1 - 111 |
| 33 | ALT LED (Aeon) | T8 Tube V4 T03RNP23ES-19 | 22.5 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 11 | 1 - 20 |
| 34 | ALT LED (Aeon) | T8 Tube V4 T03RNP46ES-19 | 46.0 | Internal | Trailing Edge | 1 - 2 | 1 - 3 | 1 - 3 | 1 - 7 | 1 - 12 |
| 35 | ALT LED (Aeon) | V2.5 GU10/GZ10 | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 37 |
| 36 | ALT LED (Aeon) | MR16 7W | 7.0 | Pharox Transformer | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 37 | ALTSA | TL DL 610W 40KC | 10.0 | ALTSA 300mA driver | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|----|------------|-----------------------------|------|-----------------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 38 | ALTSA | TL DL 630W 40KC | 30.0 | ALTSA 750mA driver | Trailing Edge | 1 - 2 | 1 - 3 | 1 - 3 | 1 - 7 | 1 - 13 |
| 39 | Apollo | TSL91E164D A80 (E27) | 7.0 | Internal | Trailing Edge | 2 - 7 | 2 - 12 | 2 - 13 | 2 - 27 | 2 - 48 |
| 40 | Apollo | TSL91E165D A80 (E27) | 10.0 | Internal | Trailing Edge | 2 - 6 | 2 - 11 | 2 - 12 | 2 - 24 | 2 - 43 |
| 41 | Applo | DIM MR16 GU10 | 5.0 | Internal | Trailing Edge | 2 - 14 | 2 - 23 | 2 - 26 | 2 - 51 | 2 - 91 |
| 42 | Applo | GU10 5W | 5.0 | Internal | Trailing Edge | 2 - 15 | 2 - 26 | 2 - 29 | 2 - 56 | 2 - 99 |
| 43 | Aurora | Candle E14 | 5.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 44 | Aurora | PAR16 GU10 (AU-DGU106A/30) | 6.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 38 | 1 - 68 |
| 45 | Aurora | PAR16 GU10 | 6.5 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 46 | Aurora | PAR16 GU10 (FLG GU10WD) | 6.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 32 | 1 - 58 |
| 47 | Aurora | PAR16 GU10 (FLG GU10WD) | 6.0 | Internal | Leading Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 8 | 1 - 14 |
| 48 | Aurora | FLCDL19CD | 19.0 | Aurora 19W LED driver | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 15 | 1 - 27 |
| 49 | Aurora | PAR16 GU10 (AU-DGU1040W/30) | 4.0 | Internal | Leading Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 13 | 1 - 22 |
| 50 | Aurora | PAR16 GU10 (AU-DGU1085/30) | 8.5 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 51 | Aurora | PAR16 GU10 (AU-DGU1085/40) | 8.5 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 52 | Aurora | AU-DL10013AW/30 | 13.0 | Aurora AU-ALDD4015 | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |
| 53 | Aurora | AU-DL10019AW/30 | 19.0 | Aurora AU-ALDD4019 | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 15 | 1 - 26 |
| 54 | Aurora | AU-MPRO/40 – Fire Downlight | 7.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 38 | 1 - 68 |
| 55 | Aurora | EN-DGU1005/40 | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 42 |
| 56 | Aurora | EN-DGU1005/27 | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 42 |
| 57 | Aurora | EN-DDL101/27 | 8.0 | Internal | Trailing Edge | 1 - 5 | 1 - 9 | 1 - 10 | 1 - 20 | 1 - 36 |
| 58 | Aurora | EN-DGU004/30 – GU10 400lm | 4.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 59 | Aurora | EN-DGU004/40 – GU10 520lm | 4.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 60 | Aurora | EN-DGU005/27 – GU10 480lm | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 61 | Aurora | EN-DGU005/30 – GU10 520lm | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 62 | Aurora | EN-DGU005/40 – GU10 520lm | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 63 | Aurora | EN-DGU005H/27 – GU10 400lm | 5.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 64 | Aurora | EN-DGU005H/40 – GU10 440lm | 5.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 65 | Aurora | EN-DGU053/30 – GU10 500lm | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|----|------------|--|------|-------------------|-------------------------------|-------------------------|--------|--------|--------|--------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 66 | Aurora | EN-DGU1024/30 – 24deg GU10 | 10.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 67 | Aurora | EN-DGU1024/40 – 24deg GU10 | 10.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 68 | Aurora | EN-DGU1024H/40 – 24deg GU10 | 10.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 69 | Aurora | EN-DGU1038/30 - 38deg GU10 | 10.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 51 |
| 70 | Aurora | EN-DGU1038/40 - 38deg GU10 | 10.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 51 |
| 71 | Aurora | EN-DGU1038H/40 - 38deg GU10 | 10.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 51 |
| 72 | Aurora | EN-DGLSE279/27 -GLS E27 810lm | 9.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 73 | Aurora | EN-DGLSB229/27 -GLS B22 810lm | 9.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 74 | Aurora | EN-DCNDE145/27 -Candle E14 400lm | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 75 | Aurora | EN-DCNDE275/27 -Candle E27 400lm | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 76 | Aurora | EN-DCNDB225/27 -Candle B22 400lm | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 77 | Aurora | EN-DG45E145/27 -Golf Ball E14 370lm | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 78 | Aurora | EN-DG45E275/27 -Golf Ball E27 370lm | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 79 | Aurora | EN-DG45B225/27 -Golf Ball B22 400lm | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 80 | Aurora | EN-DE6PRO/40 -IP65 Fixed Fire Rated Downlight | 6.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 46 | 1 - 81 |
| 81 | Aurora | EN-DE8/40 -LED Alum. IP65 fixed Fire Downlight | 8.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 39 | 1 - 69 |
| 82 | Aurora | EN-DE82W/40 -LED Alum. Adj. Fire Downlight | 8.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 39 | 1 - 69 |
| 83 | Aurora | EN-DE82MW/40 -LED Alum. Adj. Fire Downlight | 8.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 39 | 1 - 69 |
| 84 | Aurora | EN-DDL413/40 -High Performance Downlight | 13.0 | EN-DDL413 driver | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 25 | 1 - 45 |
| 85 | Aurora | EN-DDLH413/40 -High Performance Downlight | 13.0 | EN-DDLH413 driver | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 25 | 1 - 45 |
| 86 | Aurora | EN-DDL618/40 -High Performance Downlight | 18.0 | EN-DDL618 driver | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 31 |
| 87 | Aurora | EN-DDLH618/40 -High Performance Downlight | 18.0 | EN-DDLH618 driver | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 15 | 1 - 27 |
| 88 | Aurora | EN-DDL818/40 -High Performance Downlight | 18.0 | EN-DDL818 driver | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 15 | 1 - 27 |
| 89 | Aurora | EN-DDLH818/40 -High Performance Downlight | 18.0 | EN-DDLH818 driver | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 15 | 1 - 27 |
| 90 | Aurora | EN-DDLH825/35 -High Performance Downlight | 25.0 | EN-DDLH825 driver | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 8 | 1 - 14 |
| 91 | Aurora | EN-DDLH825/40 -High Performance Downlight | 25.0 | EN-DDLH825 driver | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 8 | 1 - 14 |
| 92 | Aurora | EN-DDL840/40 -Fixed dimmable Downlight | 40.0 | EN-DDL840 driver | Trailing Edge | 1 - 2 | 1 - 3 | 1 - 3 | 1 - 6 | 1 - 12 |
| 93 | Aurora | EN-DDLH840/40 -High Performance Downlight | 40.0 | EN-DDLH840 driver | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 8 | 1 - 15 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|---------------|---|-------|--------------------|-------------------------------|-------------------------|---------|---------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 94 | Aurora | EN-DDLH1045/40 -High Performance Downlight | 45.0 | EN-DDLH1045 driver | Trailing Edge | 1 - 1 | 1 - 2 | 1 - 2 | 1 - 5 | 1 - 10 |
| 95 | Aurora | EN-DDL10/40 -3in Round Downlight | 10.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 60 |
| 96 | Aurora | EN-DDL15/40 -4in Round Downlight | 15.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 97 | Aurora | EN-DDL20/40 -6in Round Downlight | 20.0 | Internal | Trailing Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 16 | 1 - 28 |
| 98 | Aurora | EN-DDL25/40 -8in Round Downlight | 25.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 13 | 1 - 24 |
| 99 | Aurora | EN-DLB071D/30 -IP44 10mm Baffle Downlight | 7.0 | EN-DLB071D driver | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 65 |
| 100 | Aurora | EN-DLB071D/40 -IP44 10mm Baffle Downlight | 7.0 | EN-DLB071D driver | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 65 |
| 101 | Aurora | EN-DLB072D/40 -IP44 20mm Baffle Downlight | 7.0 | EN-DLB072D driver | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 65 |
| 102 | Aurora | EN-DLB101D/30 -IP44 10mm Baffle Downlight | 10.0 | EN-DLB101D driver | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 31 |
| 103 | Aurora | EN-DLB101D/40 -IP44 10mm Baffle Downlight | 10.0 | EN-DLB101D driver | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 31 |
| 104 | Aurora | EN-DLB102D/40 -IP44 20mm Baffle Downlight | 10.0 | EN-DLB102D driver | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 31 |
| 105 | Aurora | EN-DDLCX10 -IP54 3in1 Colour Switch Downlight | 10.0 | EN-DDLCX10 driver | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 40 | 1 - 70 |
| 106 | Aurora | EN-DLSMR08T/30 -IP54 Round Downlight | 8.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 48 | 1 - 86 |
| 107 | Aurora | EN-DLSMR08T/40 -IP54 Round Downlight | 8.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 48 | 1 - 86 |
| 108 | Aurora | EN-DLSMR15T/40 -IP54 Round Downlight | 15.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 38 |
| 109 | Aurora | EN-DLSMR18T/40 -IP54 Round Downlight | 18.0 | Internal | Trailing Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 16 | 1 - 29 |
| 110 | Aurora | EN-PL06B/30 - Round Panel lamp | 6.0 | EN-PLDD06B | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 47 | 1 - 83 |
| 111 | Aurora | EN-PL09B/30 - Round Panel lamp | 9.0 | EN-PLDD09B | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 65 |
| 112 | Aurora | EN-LEDD15024 24V constant voltage driver | 150.0 | na | Trailing Edge | 0 | 0 | 0 | 1 - 2 | 1 - 3 |
| 113 | Afrison | Floodlight 10W | 10.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 114 | Bell Lighting | GU10 #05974 | 5.0 | External | Trailing Edge | 1 - 16 | 1 - 28 | 1 - 31 | 1 - 60 | 1 - 107 |
| 115 | Brightgreen | PR700 MR16 | 10.0 | External | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 32 | 1 - 57 |
| 116 | Brightlux | GU10 Spot | 4.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 45 |
| 117 | Brightlux | GU10 (092917D) | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 118 | Brightlux | GU10 | 5.0 | Internal | Trailing Edge | 1 - 2 | 1 - 3 | 1 - 3 | 1 - 6 | 1 - 11 |
| 119 | Brightlux | GU10 (GNH-AC-GU10-5W-B) | 5.0 | Internal | Trailing Edge | 1 - 19 | 1 - 32 | 1 - 36 | 1 - 70 | 1 - 123 |
| 120 | Bright Star | Bulb LED 108 G4 (12VAC/DC) | 1.5 | Verbatim LW70 | Trailing Edge | 1 - 69 | 1 - 120 | 1 - 133 | 1 - 257 | 1 - 456 |
| 121 | Bright Star | Bulb LED 109 G4 (12VAC/DC) | 1.5 | Verbatim LW70 | Trailing Edge | 1 - 69 | 1 - 120 | 1 - 133 | 1 - 257 | 1 - 456 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-------------|---------------------|-----|----------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 122 | Bright Star | Bulb LED 110 G9 | 3.5 | Internal | Trailing Edge | 2 - 26 | 2 - 44 | 2 - 49 | 2 - 95 | 2 - 169 |
| 123 | Bright Star | Bulb LED 111 G9 | 3.5 | Internal | Trailing Edge | 2 - 26 | 2 - 44 | 2 - 49 | 2 - 95 | 2 - 169 |
| 124 | Bright Star | Bulb LED 128 GU10 | 5.0 | Internal | Trailing Edge | 2 - 14 | 2 - 23 | 2 - 26 | 2 - 51 | 2 - 91 |
| 125 | Bright Star | Bulb LED 128 GU10 | 5.0 | Internal | Leading Edge | 2 - 11 | 2 - 19 | 2 - 21 | 2 - 40 | 2 - 72 |
| 126 | Bright Star | Bulb LED 145 GU10 | 5.0 | Internal | Trailing Edge | 2 - 15 | 2 - 26 | 2 - 29 | 2 - 57 | 2 - 101 |
| 127 | Bright Star | Bulb LED 146 GU10 | 5.0 | Internal | Trailing Edge | 2 - 17 | 2 - 29 | 2 - 32 | 2 - 62 | 2 - 111 |
| 128 | Bright Star | Bulb LED 187 R75 | 9.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 129 | Bright Star | Bulb LED 190 Candle | 4.5 | Internal | Trailing Edge | 2 - 18 | 2 - 31 | 2 - 34 | 2 - 66 | 2 - 116 |
| 130 | Bright Star | Bulb LED 191 Candle | 4.5 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 131 | Bright Star | Bulb LED 192 Candle | 4.5 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 132 | Bright Star | Bulb LED 193 Candle | 4.5 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 133 | Bright Star | Bulb LED 194 Candle | 4.5 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 134 | Bright Star | Bulb LED 195 Candle | 4.5 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 135 | Bright Star | Bulb LED 196 | 6.0 | Internal | Trailing Edge | 2 - 14 | 2 - 24 | 2 - 27 | 2 - 52 | 2 - 92 |
| 136 | Bright Star | Bulb LED 230 Candle | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 137 | Bright Star | Bulb LED 231 Candle | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 138 | Bright Star | Bulb LED 232 Candle | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 139 | Bright Star | Bulb LED 233 Candle | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 140 | Bright Star | Bulb LED 234 Candle | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 141 | Bright Star | Bulb LED 235 Candle | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 142 | Bright Star | Bulb LED 236 Bulb | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 143 | Bright Star | Bulb LED 237 Bulb | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 144 | Bright Star | Bulb LED 238 Bulb | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 145 | Bright Star | Bulb LED 239 Bulb | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 146 | Bright Star | Bulb LED 240 Bulb | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 147 | Bright Star | Bulb LED 241 Bulb | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 148 | Bright Star | Bulb LED 242 Bulb | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 149 | Bright Star | Bulb LED 243 Bulb | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-------------|---------------------------------|------|---------------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 150 | Bright Star | Bulb LED 244 Bulb | 4.5 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 151 | Bright Star | Bulb LED 245 | 8.0 | Internal | Trailing Edge | 2 - 12 | 2 - 21 | 2 - 23 | 2 - 44 | 2 - 78 |
| 152 | Bright Star | Bulb LED 246 Bulb | 8.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 38 | 1 - 67 |
| 153 | Bright Star | Bulb LED 247 Bulb | 8.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 43 | 1 - 76 |
| 154 | Bright Star | Bulb LED 248 Bulb | 8.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 43 | 1 - 76 |
| 155 | Bright Star | Bulb LED 249 Bulb | 8.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 65 |
| 156 | Bright Star | Bulb LED 250 Bulb | 8.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 65 |
| 157 | Bright Star | Bulb LED 268 GU10 | 5.0 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 55 | 1 - 98 |
| 158 | Bright Star | Bulb LED 269 Bulb | 8.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 61 |
| 159 | Bright Star | Bulb LED 270 Bulb | 8.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 61 |
| 160 | Bright Star | Bulb LED 271 Bulb | 8.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 61 |
| 161 | Bright Star | Bulb LED 272 Bulb | 8.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 61 |
| 162 | Bright Star | DL703 Panel LED lamp | 12.0 | XT-8-12W-1806 diver | Trailing Edge | 2 - 5 | 2 - 9 | 2 - 10 | 2 - 20 | 2 - 35 |
| 163 | Brilliance | l4Light 5W GU10 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 52 | 1 - 93 |
| 164 | Calex | 421594 LED Lamp 1020lm | 12.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 46 |
| 165 | Calex | 425414 Filament Rustic 320lm | 4.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 90 |
| 166 | Calex | 425464 Filament Globe 320lm | 4.0 | Internal | Trailing Edge | 1 - 18 | 1 - 31 | 1 - 34 | 1 - 66 | 1 - 116 |
| 167 | Calex | 425468 Filament Globe 650lm | 6.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 46 | 1 - 81 |
| 168 | Calex | 425484 Filament Globe 320lm | 4.0 | Internal | Trailing Edge | 1 - 18 | 1 - 31 | 1 - 34 | 1 - 66 | 1 - 116 |
| 169 | Calex | 425491 Filament Tube 310lm | 3.5 | Internal | Trailing Edge | 1 - 25 | 1 - 42 | 1 - 47 | 1 - 91 | 1 - 162 |
| 170 | Calex | 425492 Filament Tube 320lm | 4.0 | Internal | Trailing Edge | 1 - 19 | 1 - 33 | 1 - 37 | 1 - 72 | 1 - 127 |
| 171 | Calex | 425493 Filament Tube 400lm | 4.0 | Internal | Trailing Edge | 1 - 19 | 1 - 33 | 1 - 37 | 1 - 72 | 1 - 127 |
| 172 | Calex | 425496 Filament Tube 350lm | 4.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 90 |
| 173 | Calex | 425732 Filament Flex GLS 200lm | 4.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 174 | Calex | 425782 Filament Globe 200lm | 4.0 | Internal | Trailing Edge | 1 - 18 | 1 - 31 | 1 - 34 | 1 - 66 | 1 - 116 |
| 175 | Calex | 474483 Filament Spherical 350lm | 3.5 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 176 | Calex | 474484 Filament Spherical 350lm | 4.0 | Internal | Trailing Edge | 1 - 25 | 1 - 42 | 1 - 47 | 1 - 91 | 1 - 162 |
| 177 | Calex | 474490 Filament Candle 350lm | 3.5 | Internal | Trailing Edge | 1 - 25 | 1 - 42 | 1 - 47 | 1 - 91 | 1 - 162 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-------------------|-------------------------------------|------|----------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 178 | Calex | 474509 Filament GLS 810lm | 7.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 45 | 1 - 79 |
| 179 | Calex | 474510 Filament GLS 810lm | 7.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 38 | 1 - 68 |
| 180 | Calibre LED | PAR20 E27 40D Dim | 8.5 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 181 | Calibre LED | ST64 LED 3W E27 | 3.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 182 | Calibre LED | T45 LED 3W E27 | 3.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 183 | Calibre LED | G95 LED 3W E27 | 3.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 184 | Calibre LED | G45 LED 4W E27 Filament | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 185 | Calibre LED | LD0010 Adjustable Down Light 9W | 9.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 33 | 1 - 58 |
| 186 | Candela | GU10 short | 5.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 48 | 1 - 86 |
| 187 | Citizen | COB Series | 17.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 37 |
| 188 | Daylight Lighting | LED Stixx lamp (830) WW ES/BC | 9.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 189 | Daylight Lighting | LED Stixx lamp (865) daylight ES/BC | 9.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 190 | Daylight Lighting | LED GU10 DDL018 | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 87 |
| 191 | Daylight Lighting | LED GU10 DDL020 | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 87 |
| 192 | Daylight Lighting | LED Candle DDL035 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 90 |
| 193 | Daylight Lighting | LED Candle DDL036 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 90 |
| 194 | Diall LED | 5W GU10 | 5.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 48 | 1 - 86 |
| 195 | Diall LED | Candle B22 470lm | 5.9 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 196 | Diall LED | Candle E14 470lm | 6.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 197 | Diall LED | Bulb B22 1521lm | 14.5 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 22 | 1 - 38 |
| 198 | DK Lighting | GU10 CL-0002 | 5.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 25 | 1 - 44 |
| 199 | Duracell | Candle | 3.5 | Internal | Trailing Edge | 1 - 23 | 1 - 40 | 1 - 44 | 1 - 86 | 1 - 152 |
| 200 | Duracell | Candle | 3.5 | Internal | Leading Edge | 1 - 23 | 1 - 40 | 1 - 44 | 1 - 86 | 1 - 152 |
| 201 | Duracell | Mini Globe | 3.5 | Internal | Trailing Edge | 1 - 23 | 1 - 40 | 1 - 44 | 1 - 86 | 1 - 152 |
| 202 | Duracell | Mini Globe | 3.5 | Internal | Leading Edge | 1 - 23 | 1 - 40 | 1 - 44 | 1 - 86 | 1 - 152 |
| 203 | Duracell | A-Shape | 6.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 204 | Duracell | A-Shape | 6.0 | Internal | Leading Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 11 | 1 - 19 |
| 205 | Duracell | GU10 Spot (Al housing) | 5.0 | Internal | Leading Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|----------------|---------------------------------|------|--------------------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 206 | Duracell | GU10 Spot (Plastic housing) | 5.0 | Internal | Leading Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 17 | 1 - 31 |
| 207 | Eagle Lighting | GU10 GTL084 | 5.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 208 | Eagle Lighting | GU10 WXX914 | 7.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 38 | 1 - 68 |
| 209 | Eagle Lighting | GU10 WXX915 | 7.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 38 | 1 - 68 |
| 210 | Eagle Lighting | GU10 WXX900 (Dim to warm) | 5.0 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 55 | 1 - 98 |
| 211 | Eagle Lighting | LED downlight WXX102 | 7.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 61 |
| 212 | Eagle Lighting | LED grille light KK1919 | 7.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 65 |
| 213 | Eagle Lighting | LED downlight KK1936/D | 12.0 | Osram OTE 13 350mA | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 214 | Eagle Lighting | LED downlight Module KK1942 | 8.0 | KOE KLP8-120D 120mA | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 60 |
| 215 | Eagle Lighting | LED downlighter KK1966/D-9D | 9.0 | KOE KLP500x6D 500mA | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 55 |
| 216 | Eagle Lighting | LED downlighter KK1967/D-9D | 9.0 | KOE KLP500-10D 500mA | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 53 |
| 217 | Eagle Lighting | LED downlight JIN200 | 10.0 | Actec D2309NT-N3 230mA | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 60 |
| 218 | Eagle Lighting | LED downlight L-CL-0107 WXX103 | 7.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 219 | Eagle Lighting | Round LED downlight TLQS4C | 6.0 | Eagle 6W dimmable driver | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 55 |
| 220 | Earth Power | Black Max GU10 | 5.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 11 | 1 - 20 |
| 221 | EcoLED | GU10 | 5.0 | Internal | Trailing Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 17 | 1 - 30 |
| 222 | EcoLED | GU10 DIM | 5.0 | Internal | Leading Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 22 |
| 223 | EcoLED | GU10 DIM | 7.0 | Internal | Leading Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 38 |
| 224 | EcoLED | GU10 | 6.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 11 | 1 - 19 |
| 225 | EcoLED | GU10 | 9.0 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 19 | 1 - 34 |
| 226 | EcoLED | MR16 3W | 3.0 | Pharox Transformer | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 39 | 1 - 70 |
| 227 | EcoLED | MR16 6W | 6.0 | Pharox Transformer | Trailing Edge | 1 - 11 | 1 - 18 | 1 - 20 | 1 - 39 | 1 - 70 |
| 228 | Ellies | FLGU10C (non-dimmable) | 3.5 | Internal | Trailing Edge | 1 - 16 | 1 - 27 | 1 - 30 | 1 - 59 | 1 - 104 |
| 229 | Ellies | FLGU10C (non-dimmable) | 4.0 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 52 | 1 - 92 |
| 230 | Ellies | FLGU10CD | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 54 | 1 - 95 |
| 231 | Ellies | FL24W15T8DL (non-dimmable) | 24.0 | Internal | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 15 | 1 - 27 |
| | Enlite | See Aurora above | | | | | | | | |
| 232 | Enviro-Bulb | E55-GU-35WWD (GU10 3000K) 90059 | 5.5 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 41 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-------------|----------------------------------|------|----------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 233 | Enviro-Bulb | E55-GU-35CWD (GU10 4000K) 90060 | 5.5 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 41 |
| 234 | Enviro-Bulb | E55-GU-35DWD (GU10 5000K) 90061 | 5.5 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 41 |
| 235 | Enviro-Bulb | E55C-E14-WWD (E14 2700K) 90038 | 5.5 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 24 | 1 - 43 |
| 236 | Enviro-Bulb | E55C-E27-WWD (E27 2700K) 90039 | 5.5 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 24 | 1 - 43 |
| 237 | Enviro-Bulb | E55C-B22-WWD (B22 2700K) 90043 | 5.5 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 24 | 1 - 43 |
| 238 | Eurolux | G727CW-LED-GU10 | 7.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 38 |
| 239 | Eurolux | G478CW GU10 Classic | 7.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 39 | 1 - 69 |
| 240 | Eurolux | G478WW GU10 Classic | 7.0 | Internal | Trailing Edge | 1 - 12 | 1 - 20 | 1 - 22 | 1 - 43 | 1 - 76 |
| 241 | Eurolux | G1036CW GU10 Premium | 6.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 47 | 1 - 83 |
| 242 | Eurolux | G1036CW GU10 Premium | 7.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 243 | Eurolux | G1036WW GU10 Premium | 7.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 38 | 1 - 68 |
| 244 | Eurolux | G1036DL GU10 Premium | 6.5 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 43 | 1 - 76 |
| 245 | Eurolux | G1039CW B22 Premium Globe | 9.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 53 |
| 246 | Eurolux | G1039WW B22 Premium Globe | 9.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 53 |
| 247 | Eurolux | G1040CW E27 Premium Globe | 9.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 55 |
| 248 | Eurolux | G1040WW E27 Premium Globe | 9.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 55 |
| 249 | Eurolux | G1037Sww Candle GU10 Premium | 5.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 250 | Eurolux | G1037Bww Candle GU10 Premium | 5.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 251 | Eurolux | G1037Eww Candle GU10 Premium | 5.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 252 | Eurolux | G1038Eww E27 Premium Globe | 5.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 253 | Eurolux | G1038Bww B22 Premium Globe | 5.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 254 | Eurolux | G977 Candle | 6.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 255 | Eurolux | G952 Candle | 6.0 | Internal | Trailing Edge | 1 - 16 | 1 - 28 | 1 - 31 | 1 - 61 | 1 - 108 |
| 256 | Eurolux | G639ES (E27 Filament Candle) | 4.0 | Internal | Trailing Edge | 1 - 19 | 1 - 33 | 1 - 37 | 1 - 72 | 1 - 127 |
| 257 | Eurolux | G639SES (E14 Filament Candle) | 4.0 | Internal | Trailing Edge | 1 - 19 | 1 - 33 | 1 - 37 | 1 - 72 | 1 - 127 |
| 258 | Eurolux | G639BC (B22 Filament Candle) | 4.0 | Internal | Trailing Edge | 1 - 19 | 1 - 33 | 1 - 37 | 1 - 72 | 1 - 127 |
| 259 | Eurolux | G990WW (E27 Filament Maxi Globe) | 13.0 | Internal | Trailing Edge | 1 - 7 | 1 - 13 | 1 - 14 | 1 - 28 | 1 - 50 |
| 260 | Eurolux | G991WW (G9 LED) | 4.0 | Internal | Trailing Edge | 1 - 19 | 1 - 33 | 1 - 37 | 1 - 72 | 1 - 127 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-------------|--------------------------------|------|----------|-------------------------------|-------------------------|--------|--------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 261 | Eurolux | G1124CW (E14 R50 LED) | 5.0 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 55 | 1 - 97 |
| 262 | Eurolux | G1125WW (B15 Candle LED) | 5.0 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 55 | 1 - 97 |
| 263 | Eurolux | G1126WW (E14 Filament Candle) | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 50 | 1 - 89 |
| 264 | Eurolux | G1126CW (E14 Filament Candle) | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 50 | 1 - 89 |
| 265 | Eurolux | Carbon Filament E27 | 60.0 | Internal | Trailing Edge | 1 - 2 | 1 - 3 | 1 - 4 | 1 - 8 | 1 - 13 |
| 266 | Flash | GU10 (600 969 636 8382) | 7.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 22 |
| 267 | Flash | GU10 (600 969 636 9945) | 7.0 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 32 |
| 268 | Flash | LED Filament ST64 Pear E27 | 4.0 | Internal | Trailing Edge | 1 - 28 | 1 - 49 | 1 - 54 | 1 - 105 | 1 - 187 |
| 269 | Futurelight | GU10 5W Spot | 5.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 25 | 1 - 44 |
| 270 | GAP | SMD LED GU10 | 6.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 21 |
| 271 | GC | GU10 (LED CUP) | 6.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 21 |
| 272 | GC | GU10 VLC-1005Z | 6.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 21 |
| 273 | GC | GU10 LED Spot Light | 6.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 274 | GE | GU10 | 6.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 41 | 1 - 73 |
| 275 | GE | Candle E14 270lm | 4.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 90 |
| 276 | Genesis One | GU10D63 | 6.3 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 55 | 1 - 98 |
| 277 | Genesis One | GU10D7 | 7.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 87 |
| 278 | Genesis One | CAND5/27/E14 (Filament Candle) | 5.0 | Internal | Trailing Edge | 1 - 16 | 1 - 27 | 1 - 30 | 1 - 58 | 1 - 103 |
| 279 | Genstar | GEN5WGU10 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 90 |
| 280 | Genstar | GEN7WGU10 | 7.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 281 | GEP Power | GU10 460lm | 6.5 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 28 | 1 - 51 |
| 282 | GEP Power | GU10 556lm | 7.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 28 | 1 - 51 |
| 283 | G Light | GU10 36D | 6.5 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 35 | 1 - 63 |
| 284 | G Light | GU10 36D 4000K | 6.5 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 45 | 1 - 79 |
| 285 | G Light | GU10 36D ECO 4000K | 7.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 43 | 1 - 76 |
| 286 | Giantlight | LED Panel, AC 72x LED's | 40.0 | Internal | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 10 | 1 - 17 |
| 287 | GL Lighting | LED Tube T8G06-524-3 | 24.0 | Internal | Leading Edge | 1 - 1 | 1 - 2 | 1 - 2 | 1 - 4 | 1 - 7 |
| 288 | Hi-Tech | FXCGU10 | 7.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 45 | 1 - 80 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-------------|--|------|----------|-------------------------------|-------------------------|--------|--------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 289 | Hello Today | HD-DLB07W GU10 | 7.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 46 | 1 - 81 |
| 290 | Havells | BrightFill Filament Candle | 5.0 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 55 | 1 - 98 |
| 291 | Havells | BrightFill Filament A60 | 7.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 292 | Havells | GU10 865 Dim | 6.5 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 32 | 1 - 57 |
| 293 | Hoi P'loy | Petite Pear Incandescent (LB-PP-11W) | 11.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 294 | Hoi P'loy | Vintage Edison filament spiral | 40.0 | Internal | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 9 | 1 - 17 |
| 295 | Hoi P'loy | Vintage Edison filament squirrel cage | 40.0 | Internal | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 9 | 1 - 17 |
| 296 | Hoi P'loy | Vintage Edison filament classic spiral (small) | 40.0 | Internal | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 9 | 1 - 17 |
| 297 | Hoi P'loy | Vintage Edison filament squirrel cage (medium) | 40.0 | Internal | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 9 | 1 - 17 |
| 298 | Hoi P'loy | LB-LED-XL-TD-E27 | 4.0 | Internal | Trailing Edge | 1 - 21 | 1 - 36 | 1 - 40 | 1 - 77 | 1 - 137 |
| 299 | Hoi P'loy | LB-LED-XL-SQ-E27 | 10.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 300 | Hoi P'loy | LB-LED-XL-SP-E27 | 3.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 160 |
| 301 | Hoi P'loy | LB-LED-L-FA-E27 | 2.5 | Internal | Trailing Edge | 1 - 33 | 1 - 57 | 1 - 63 | 1 - 121 | 1 - 215 |
| 302 | Hoi P'loy | LB-LED-L-H-E27 | 3.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 160 |
| 303 | Hoi P'loy | LB-LED-PP-O-E27 | 3.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 160 |
| 304 | Hoi P'loy | LB-LED-L-SP-E27 | 3.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 160 |
| 305 | Hoi P'loy | LB-LED-L-SQ-E27 | 6.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 63 | 1 - 112 |
| 306 | Hoi P'loy | LB-LED-M-SP-E27 | 3.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 160 |
| 307 | Hoi P'loy | LB-LED-M-SQ-E27 | 6.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 63 | 1 - 112 |
| 308 | Hoi P'loy | LB-LED-VS-E27 | 3.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 160 |
| 309 | Hoi P'loy | LB-LED-TH-S-E27 | 3.0 | Internal | Trailing Edge | 1 - 21 | 1 - 36 | 1 - 40 | 1 - 77 | 1 - 137 |
| 310 | Hoi P'loy | LB-LED-TH-L-E7 | 4.0 | Internal | Trailing Edge | 1 - 21 | 1 - 36 | 1 - 40 | 1 - 77 | 1 - 137 |
| 311 | Hoi P'loy | LB-LED-TS-S-E27 | 3.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 160 |
| 312 | Hoi P'loy | LB-LED-TS-L-E27 | 4.0 | Internal | Trailing Edge | 1 - 21 | 1 - 36 | 1 - 40 | 1 - 77 | 1 - 137 |
| 313 | Hoi P'loy | LB-LED-TH-XL-E7 | 4.0 | Internal | Trailing Edge | 1 - 21 | 1 - 36 | 1 - 40 | 1 - 77 | 1 - 137 |
| 314 | Hoi P'loy | LB-LED-TS-XL-E27 | 4.0 | Internal | Trailing Edge | 1 - 21 | 1 - 36 | 1 - 40 | 1 - 77 | 1 - 137 |
| 315 | Hoi P'loy | LB-LED-RS-E27 | 3.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 160 |
| 316 | Hoi P'loy | LB-LED-SQ-S-E27 | 3.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 160 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-------------|----------------------------------|------|-----------------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 317 | Hoi P'loy | LB-LED-SQ-H-E27 | 3.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 160 |
| 318 | Hoi P'loy | LB-LED-L-FR-E27 | 6.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 63 | 1 - 112 |
| 319 | Hoi P'loy | LB-LED-M-FR-E27 | 6.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 63 | 1 - 112 |
| 320 | Hoi P'loy | LB-LED-S-FR-E27 | 6.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 63 | 1 - 112 |
| 321 | Hoi P'loy | LB-LED-L-OP-E27 | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 87 |
| 322 | Hoi P'loy | LB-LED-M-OP-E27 | 5.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 87 |
| 323 | Hoi P'loy | LB-LED-S-OP-E27 | 5.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 87 |
| 324 | Hoi P'loy | LB-LED-XL-OP-E27 | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 87 |
| 325 | Hoi P'loy | LB-LED-XL-FR-E27 | 6.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 63 | 1 - 112 |
| 326 | Hoi P'loy | LB-LED--XL-BA- E27 | 6.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 63 | 1 - 112 |
| 327 | Hoi P'loy | Petite Pear LED | 3.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 160 |
| 328 | Huayi | SAGU02073 | 7.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 87 |
| 329 | InterEnergy | GU10 "Silver" | 5.0 | Internal | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 9 | 1 - 17 |
| 330 | InterEnergy | GU10 "White" | 5.0 | Internal | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 9 | 1 - 17 |
| 331 | InterEnergy | K50 | 12.0 | External (K50 Driver) | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 14 | 1 - 25 |
| 332 | InterEnergy | G50 | 8.0 | External (G50 Driver) | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 65 |
| 333 | InterEnergy | B80 | 12.0 | External (B80 Driver) | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 14 | 1 - 25 |
| 334 | Johnson | GU10 (WW & CW) | 6.0 | Internal | Leading Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 11 | 1 - 19 |
| 335 | K. Light | GU10 (COB 550lm) | 7.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 50 | 1 - 89 |
| 336 | K. Light | Candle Filament E14 (HX-CN35-4W) | 4.0 | Internal | Trailing Edge | 1 - 16 | 1 - 28 | 1 - 31 | 1 - 60 | 1 - 107 |
| 337 | K. Light | Filament Bulb UF-L01761-D | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 338 | K. Light | Filament Bulb HX-CW35-4W | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 339 | K. Light | Filament Bulb HX-CN35-4W | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 340 | K. Light | Filament Bulb HX-GB45-4W | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 341 | K. Light | Filament Bulb HX-GL45-4W | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 342 | K. Light | Filament Bulb HX-LST30-185-4W | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 343 | K. Light | Filament Bulb HX-LA60-4W/CW | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 344 | K. Light | Filament Bulb HX-LA60-4W | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|------------|--|-----|----------|-------------------------------|-------------------------|--------|--------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 345 | K. Light | Filament Bulb HX-LA60-4W/OPAL | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 346 | K. Light | Filament Bulb HX-LST64-4W | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 347 | K. Light | Filament Bulb HX-LSAST64-4W | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 348 | K. Light | Filament Bulb HX-LSG80-4W | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 349 | K. Light | Filament Bulb HX-LSG95-4W | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 350 | K. Light | Filament Bulb HX-G125-4W | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 351 | K. Light | Filament Bulb HX-LG125-4W | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 352 | K. Light | Filament Bulb HX-LA60-8W | 8.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 28 | 1 - 51 |
| 353 | Krillux | GUL016 GU10 Glass 3000K | 6.0 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 55 | 1 - 97 |
| 354 | Krillux | GUL017 GU10 Glass 4000K | 6.0 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 55 | 1 - 97 |
| 355 | Krillux | GUL018 GU10 Glass 6000K | 6.0 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 55 | 1 - 97 |
| 356 | Krillux | GUL023 GU10 3000K | 5.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 56 | 1 - 100 |
| 357 | Krillux | GUL024 GU10 4000K | 5.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 56 | 1 - 100 |
| 358 | Krillux | GUL025 GU10 6000K | 5.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 56 | 1 - 100 |
| 359 | Krillux | LEC007 LED G9 GLASS 3000K | 2.5 | Internal | Trailing Edge | 1 - 31 | 1 - 53 | 1 - 59 | 1 - 115 | 1 - 204 |
| 360 | Krillux | LEC008 LED G9 GLASS 4000K | 2.5 | Internal | Trailing Edge | 1 - 31 | 1 - 53 | 1 - 59 | 1 - 115 | 1 - 204 |
| 361 | Krillux | LEC009 LED G9 GLASS 6000K | 2.5 | Internal | Trailing Edge | 1 - 31 | 1 - 53 | 1 - 59 | 1 - 115 | 1 - 204 |
| 362 | Krillux | GU10 EVE001 | 5.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 363 | Krillux | PEG005 E27 LED PEAR AMBER 2200K | 4.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 364 | Krillux | OPG007 E27 LED OPALINA AMBER 2200K G95 | 4.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 365 | Krillux | OPG008 E27 OPALINA FILAMENT 3000K G125 | 8.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 366 | Krillux | OPG009 E27 OPALINA FILAMENT 4000K G125 | 8.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 367 | Krillux | CAP010 Candle E14 3000K | 5.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 368 | Krillux | CAP011 Candle E14 4000K | 5.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 369 | Krillux | CAG021 E14 CANDLE FILAMENT 3000K. | 4.0 | Internal | Trailing Edge | 1 - 19 | 1 - 33 | 1 - 37 | 1 - 72 | 1 - 127 |
| 370 | Krillux | CAG021 E14 CANDLE FILAMENT 4000K | 4.0 | Internal | Trailing Edge | 1 - 19 | 1 - 33 | 1 - 37 | 1 - 72 | 1 - 127 |
| 371 | Krillux | CAG022 C35 E14 CANDLE FILAMENT 4000K | 4.0 | Internal | Trailing Edge | 1 - 19 | 1 - 33 | 1 - 37 | 1 - 72 | 1 - 127 |
| 372 | Landmark | RL-5WD-15WW | 5.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 21 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|--------------------|----------------------------|------|-----------------------|-------------------------------|-------------------------|--------|--------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 373 | LDC | GU10 (001510) | 5.0 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 55 | 1 - 98 |
| 374 | LDC | GU10 (001511) | 5.0 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 55 | 1 - 97 |
| 375 | LDC | GU10 (001515/D) | 6.0 | Internal | Trailing Edge | 1 - 12 | 1 - 20 | 1 - 22 | 1 - 43 | 1 - 76 |
| 376 | LDC | DLV-R 3 inch downlight | 13.0 | Actec D3501U 350mA | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 32 |
| 377 | LDC | DLV-R 3 inch downlight | 14.0 | Actec D50022U 500mA | Trailing Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 17 | 1 - 30 |
| 378 | Ledionopto | GU10C | 7.0 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |
| 379 | Ledionopto | TD20 Series downlighter | 7.0 | 350mA driver | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 32 | 1 - 57 |
| 380 | Ledionopto | TD36 Series downlighter | 15.0 | 700mA driver | Trailing Edge | 1 - 5 | 1 - 9 | 1 - 10 | 1 - 20 | 1 - 35 |
| 381 | Ledionopto | DLV LED 25W NW | 25.0 | 700mA driver | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 8 | 1 - 15 |
| 382 | LED Lumo | GU10 | 6.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 54 |
| 383 | LED Lumo | GU10 (Aluminium housing) | 6.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 40 |
| | Ledvance | See Osram / Ledvance below | | | | | | | | |
| 384 | LEDwise | ML7-WW-36-AL-D | 9.6 | External | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 22 | 1 - 38 |
| 385 | Lightbulbmoment | LBM-G4-1.5W-PL03-DIM | 1.5 | Verbatim LW70 | Trailing Edge | 1 - 41 | 1 - 70 | 1 - 78 | 1 - 151 | 1 - 268 |
| 386 | Lightbulbmoment | LBM-GU10-4.5W-DIM | 4.5 | Internal | Leading Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 11 | 1 - 19 |
| 387 | Lightbulbmoment | LBM-GU10-5W-DIM | 5.0 | Internal | Leading Edge | 1 - 5 | 1 - 9 | 1 - 10 | 1 - 20 | 1 - 36 |
| 388 | Lightbulbmoment | LBM-GU10-7.5W-DIM | 7.5 | Internal | Leading Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 21 |
| 389 | Lightnet | MGM Gimbal 840 36D 300680 | 25.0 | Tridonic LCBI 25W | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 21 |
| 390 | Lightnet | DLV Downlight 6 inch | 25.0 | AcTech D70040NT 700mA | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 22 |
| 391 | Limelight | GU10 380lm | 4.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 11 | 1 - 20 |
| 392 | Lights by Linea | Model 7" | 17.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 22 | 1 - 39 |
| 393 | Light Leader (GEP) | GU10-CY2-D | 4.5 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |
| 394 | Light Leader (GEP) | GU10-COB-YZ-D | 7.5 | Internal | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 14 | 1 - 25 |
| 395 | Lightspot | Littleou 420lm GU10 | 6.0 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 53 | 1 - 94 |
| 396 | Lighting Warehouse | G9 LED (6009707428333) | 4.5 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 397 | Li Zhou | Panel LED 3W | 3.0 | Li Zhou 4W Driver | Leading Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 22 |
| 398 | Li Zhou | Panel LED 6W | 6.0 | Li Zhou 7W Driver | Leading Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 10 | 1 - 18 |
| 399 | Li Zhou | Panel LED 9W | 9.0 | Li Zhou 15W Driver | Leading Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 9 | 1 - 16 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|--------------|--------------------------------|-----|-----------------|-------------------------------|-------------------------|--------|--------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 400 | LMR Lighting | GU10 | 6.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 51 |
| 401 | LMR Lighting | GU10 | 7.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 37 |
| 402 | Lucent | GU10 7WD | 7.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 48 | 1 - 86 |
| 403 | Lucent | E27 Candle 5WD | 5.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 404 | Luc-Eco | GU10 (LGDW5W37-01) | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |
| 405 | Luc-Eco | GU10 (LGDW5W37-01) | 5.0 | Internal | Leading Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 13 | 1 - 24 |
| 406 | Luc-Eco | GU10 (LGU5W380D40W-01) | 5.0 | Internal | Leading Edge | 1 - 5 | 1 - 9 | 1 - 10 | 1 - 20 | 1 - 36 |
| 407 | Lumaglo | G5-GU10/5.5/DC | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 408 | Lumax | LUM-GU10-SMD-SH-4.5W | 4.5 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 52 | 1 - 92 |
| 409 | Lumax | LUM-GU10-COB-SU-5W | 5.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 88 |
| 410 | Lumax | GU10 WW | 4.5 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 411 | Lumax | GU10 (Single LED) | 5.0 | Internal | Trailing Edge | 1 - 5 | 1 - 9 | 1 - 10 | 1 - 20 | 1 - 35 |
| 412 | Lumax | GU10 SMD 2835 | 7.5 | Internal | Trailing Edge | 3 - 14 | 3 - 24 | 3 - 27 | 3 - 54 | 3 - 95 |
| 413 | Lumax | GU10 (Single LED) | 8.0 | Internal | Trailing Edge | 3 - 5 | 3 - 8 | 3 - 9 | 3 - 18 | 3 - 33 |
| 414 | Lumax | A60 Bulb | 7.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 45 |
| 415 | Lumax | A60 Bulb SMD 2835 | 9.5 | Internal | Trailing Edge | 3 - 9 | 3 - 15 | 3 - 17 | 3 - 34 | 3 - 60 |
| 416 | Lumax | E14 Candle | 3.0 | Internal | Trailing Edge | 1 - 33 | 1 - 57 | 1 - 63 | 1 - 121 | 1 - 215 |
| 417 | Lumax | GU10 30SMD | 5.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 74 | 1 - 132 |
| 418 | Lumax | GU10 (Glass) | 5.5 | Internal | Trailing Edge | 1 - 21 | 1 - 36 | 1 - 40 | 1 - 77 | 1 - 136 |
| 419 | Lumax | GU10 (LUM-GUDCG/05) – Glass | 5.0 | Internal | Trailing Edge | 1 - 18 | 1 - 31 | 1 - 34 | 1 - 65 | 1 - 116 |
| 420 | Lumax | Candle E14 (LUM-CD3714/05-3K) | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 52 | 1 - 93 |
| 421 | Lumax | GU10 (LUM-GUD/055-4K) | 5.5 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 28 | 1 - 51 |
| 422 | Lumax | LM-FRP-R75-6W Frameless Panel | 6.0 | External AcTech | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 44 | 1 - 78 |
| 423 | Lumax | LM-FRP-R100-8W Frameless Panel | 8.0 | External AcTech | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 40 | 1 - 70 |
| 424 | Lumax | S11 G45 | 5.0 | Internal | Trailing Edge | 1 - 5 | 1 - 9 | 1 - 10 | 1 - 20 | 1 - 36 |
| 425 | Lumax | S11 GU10 | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |
| 426 | Lumax | S11 C37 | 5.0 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 19 | 1 - 34 |
| 427 | Lumax | S11 A60 | 9.0 | Internal | Trailing Edge | 1 - 5 | 1 - 9 | 1 - 10 | 1 - 20 | 1 - 36 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|------------|----------------------------------|------|------------------------|-------------------------------|-------------------------|--------|--------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 428 | Lumax | LUM-GD12527/025-2K Filament | 2.5 | Internal | Trailing Edge | 1 - 31 | 1 - 53 | 1 - 59 | 1 - 115 | 1 - 204 |
| 429 | Lumax | LUM-GD9527/04-2K Filament | 4.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 430 | Lumax | LUM-PSD16027/04-2K Filament | 4.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 431 | Lumax | LUM-STD6427/04-2K Filament | 4.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 432 | Lumax | LUM-CD3514/04-3K Filament Candle | 4.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 433 | Lumax | LUM-CD3527/04-3K Filament Candle | 4.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 73 | 1 - 130 |
| 434 | Lumax | LUM-GUDAW/05-3K AW GU10 DIM | 5.0 | Internal | Trailing Edge | 3 - 14 | 3 - 23 | 3 - 26 | 3 - 51 | 3 - 90 |
| 435 | Lumax | LUM-PLRD85/03-3K Dimmable Panel | 3.0 | BT-DL6901W6 | Trailing Edge | 1 - 21 | 1 - 36 | 1 - 40 | 1 - 78 | 1 - 138 |
| 436 | Lumax | LUM-PLRD120/06-3K Dimmable Panel | 6.0 | BT-DL6901W6 | Trailing Edge | 1 - 19 | 1 - 32 | 1 - 36 | 1 - 69 | 1 - 123 |
| 437 | Lumax | LUM-AD6027/06-3K A60 Dimmable | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 50 | 1 - 89 |
| 438 | Luminence | K50-R7 | 9.5 | Dimtronic 260mA driver | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 37 |
| 439 | Luxn | LED Spot GU10 | 5.0 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 440 | Major Tech | GU10 (L2A-D3W) | 3.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 22 |
| 441 | Major Tech | GU10 (L2A-D5C) | 5.0 | Internal | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 9 | 1 - 16 |
| 442 | Major Tech | GU10 (LGU10-D5W) | 5.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 11 | 1 - 19 |
| 443 | Major Tech | LED filament E14 (LFC35E14-D4W) | 4.0 | Internal | Trailing Edge | 1 - 25 | 1 - 43 | 1 - 48 | 1 - 92 | 1 - 163 |
| 444 | Major Tech | Candle E14 (LC38E14-D48W) | 4.8 | Internal | Trailing Edge | 1 - 22 | 1 - 38 | 1 - 42 | 1 - 81 | 1 - 143 |
| 445 | Major Tech | LED filament E27 (LFA60E27-D6W) | 6.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 46 |
| 446 | Major Tech | E27 (LA60E27-D7C) | 7.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 447 | Major Tech | DLW-9C | 9.0 | External (MLD-10W) | Leading Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 10 | 1 - 18 |
| 448 | Mesmerize | HL-MZ-5.5W-GU10-D | 5.5 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 11 | 1 - 19 |
| 449 | Mesmerize | HL-MZ-8W-GU10-D | 8.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 61 |
| 450 | Mesmerize | HL-UDL-003 6W Panel 300mA | 6.0 | LED-09VATDR 300mA | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 451 | Mesmerize | HL-UDL-005 12W Panel 300mA | 12.0 | LED-09VATDR 300mA | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 55 |
| 452 | Mesmerize | MLCL-6W-R-NW (Round Panel) | 6.0 | LPDD-6W (PE294B0730) | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 53 | 1 - 94 |
| 453 | Mesmerize | MLCL-12W-R-NW (Round Panel) | 12.0 | LPDD-12W (PE294B1230) | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 28 | 1 - 50 |
| 454 | Mesmerize | MLCL-18W-R-NW (Round Panel) | 18.0 | LPDD-18W (PE296B1830) | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 19 | 1 - 34 |
| 455 | Mesmerize | MLCL-24W-R-CW (Round Panel) | 24.0 | LPDD-24W (PF-292B) | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 14 | 1 - 25 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|------------|--|------|-------------------|-------------------------------|-------------------------|--------|--------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 456 | Mesmerize | Round 18W Panel 300mA | 18.0 | LED-18VATDR 300mA | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 22 | 1 - 39 |
| 457 | Mesmerize | Round 24W Panel 300mA | 24.0 | LED-24VATDR 300mA | Trailing Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 17 | 1 - 30 |
| 458 | Mesmerize | ML-DL-10W-TR | 10.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 459 | Mesmerize | ML-HG2-10W-CCT-C (3 in 1 lamp) | 10.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 60 |
| 460 | Mesmerize | ML-VF-A60-6W-D Filament Bulb | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 88 |
| 461 | Mesmerize | ML-VF-ST64-6W-D Filament Bulb | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 88 |
| 462 | Mesmerize | ML-VF-G95-6W-D Filament Bulb | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 88 |
| 463 | Mesmerize | ML-VF-G125-6W-D Filament Bulb | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 88 |
| 464 | Mesmerize | ML-Z-4.8W-GU10-2.7K-D | 4.8 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 32 |
| 465 | Mesmerize | ML-Z-4.8W-GU10-4K-D | 4.8 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 32 |
| 466 | Mesmerize | ML-Z-4.8W-GU10-6K-D | 4.8 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 32 |
| 467 | Mesmerize | ML-Z-G45-4.5W | 4.5 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 468 | Mesmerize | ML-Z-C37-4.5W | 4.5 | Internal | Trailing Edge | 1 - 25 | 1 - 43 | 1 - 48 | 1 - 94 | 1 - 166 |
| 469 | Mesmerize | ML-Z-6.8W-GU10-W | 6.8 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 55 |
| 470 | Mesmerize | ML-Z-A60-9W | 9.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 10 | 1 - 18 |
| 471 | Mesmerize | ML-A60-9W-B22-4K-D | 9.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 32 | 1 - 57 |
| 472 | Mesmerize | ML-TR-10W-CCT (Halo Trio series 3 in 1) | 10.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 32 | 1 - 57 |
| 473 | Mesmerize | ML-SRS-8W-GU10-27K-D (Sirus Series GU10) | 8.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 60 |
| 474 | Mesmerize | ML-SRS-8W-GU10-40K-D (Sirus Series GU10) | 8.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 60 |
| 475 | Mesmerize | ML-SRS-8W-GU10-65K-D (Sirus Series GU10) | 8.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 60 |
| 476 | Mesmerize | Candle C35 Filament | 2.0 | Internal | Trailing Edge | 1 - 31 | 1 - 54 | 1 - 60 | 1 - 116 | 1 - 207 |
| 477 | Mesmerize | Antique Edison Bulb ST64 | 4.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 75 | 1 - 133 |
| 478 | Mesmerize | Antique Edison Bulb G95 | 4.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 75 | 1 - 133 |
| 479 | Mesmerize | 230VAC Strip LED 1m * | 8.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 46 | 1 - 81 |
| 480 | Mesmerize | 230VAC LED Tapelight 1m (white/colour)* | 8.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 47 | 1 - 83 |
| 481 | Mesmerize | 230VAC LED Neon Flex 1m (white/colour)* | 8.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 47 | 1 - 83 |
| 482 | Mesmerize | LED Globe A60 ML-A60-9W-E27-xx-D | 9.0 | Internal | Trailing Edge | 1 - 11 | 1 - 18 | 1 - 20 | 1 - 39 | 1 - 70 |
| 483 | Mesmerize | Comet GU10 ML-CT-5.5W-GU10-xx-D | 5.5 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|--------------|---------------------------------|------|----------------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 484 | Mesmerize | Comet GU10 ML-CT-7.5W-GU10-xx-D | 7.5 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 39 | 1 - 69 |
| 485 | Meteor | GU10 | 3.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 51 |
| 486 | Meteor | GU10 | 4.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 37 |
| 487 | Meteor | GU10 | 6.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 11 | 1 - 19 |
| 488 | NVC | NLED110D (350mA) | 9.0 | Aurora 1-10W Driver | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 38 |
| 489 | NVC | NLED110D (350mA) | 9.0 | Aurora 7-10W Driver | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 53 |
| 490 | NVC | NLED111D (500mA) | 12.0 | Aurora 20W Driver | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 27 | 1 - 48 |
| 491 | NVC | G Light GU10 | 6.5 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 35 | 1 - 62 |
| 492 | NVC | LED GU10D | 7.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 41 | 1 - 73 |
| 493 | MSI | "I"GU10 | 5.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 51 |
| 494 | O-Lite / MCE | LEDGU10-6WD | 6.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 10 | 1 - 18 |
| 495 | O-Lite / MCE | GU10DIM-6W-CW/WW | 6.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 46 | 1 - 81 |
| 496 | O-Lite / MCE | OL-CY03 (Cyclops Range) | 3.0 | O-lite Mini D26004NT | Trailing Edge | 1 - 19 | 1 - 32 | 1 - 36 | 1 - 71 | 1 - 126 |
| 497 | O-Lite / MCE | OL-CY06 (Cyclops Range) | 6.0 | O-lite D26009NT | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 498 | O-Lite / MCE | OL-CY12 (Cyclops Range) | 12.0 | O-lite D26012NT | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 60 |
| 499 | O-Lite / MCE | OL-CY18 (Cyclops Range) | 18.0 | O-lite D26020NT | Trailing Edge | 1 - 5 | 1 - 9 | 1 - 10 | 1 - 20 | 1 - 35 |
| 500 | O-Lite / MCE | OL-G200-4W-D-GD/GY | 4.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 501 | O-Lite / MCE | OL-DT170-GB/O | 4.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 502 | O-Lite / MCE | OL-PS165-4W-D-6Y | 4.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 503 | O-Lite / MCE | OL-PS40-4W-D-GD/GY | 4.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 504 | O-Lite / MCE | OL-C120-4W-D-GD | 4.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 505 | O-Lite / MCE | OL-A60-4W-D-GY/T | 4.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |
| 506 | O-Lite / MCE | OL-G125-5W-D-GD | 5.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 48 | 1 - 86 |
| 507 | O-Lite / MCE | OL-G80-5W-GY/GD/T | 5.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 48 | 1 - 86 |
| 508 | O-Lite / MCE | OL-G95-5W-D-GY/GD/T | 5.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 48 | 1 - 86 |
| 509 | O-Lite / MCE | OL-A60-8W-D-GY | 8.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 54 |
| 510 | O-Lite / MCE | OL-ST64-8W-D-GY/GD/T | 8.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 54 |
| 511 | Oppl | GU10 Spot Light | 5.0 | Internal | Trailing Edge | 1 - 15 | 1 - 26 | 1 - 29 | 1 - 57 | 1 - 102 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|------------------|-------------------------------------|------|-------------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 512 | Oppl | LED-E-E27-6W-DIM | 6.0 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |
| 513 | Oppl | LED E2 GU10 6W DIM | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 514 | Oppl | GU10 Spot Light | 7.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 515 | OptiLED | Tornado GU10 5.5W | 5.5 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 22 | 1 - 39 |
| 516 | Optique | XOPT3012 | 12.0 | Actec DIM300mA | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 13 | 1 - 24 |
| 517 | Optique | OPT3012 | 12.0 | Tridonic LCA 15W | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 46 |
| 518 | Optique | XOPT2512 | 7.0 | Tridonic LCBI 14W | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 53 |
| 519 | Optique | XOPT4012A | 15.0 | Tridonic LCA 15W | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 22 | 1 - 38 |
| 520 | Osram / Ledvance | Parathom Pro PAR16 50 Advanced R | 9.5 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 38 | 1 - 68 |
| 521 | Osram / Ledvance | Parathom Pro PAR16 50 Advanced R | 10.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 61 |
| 522 | Osram / Ledvance | Parathom Pro PAR16 50 Advanced | 5.3 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 44 | 1 - 78 |
| 523 | Osram / Ledvance | Parathom Pro PAR16 50 (Adv) | 5.5 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 524 | Osram / Ledvance | Parathom Pro MR16 20 Advanced | 5.0 | HTM70 | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 525 | Osram / Ledvance | Parathom Pro MR16 35 Advanced | 5.9 | HTM70, ETP70 | Trailing Edge | 2 - 12 | 2 - 21 | 2 - 23 | 2 - 47 | 2 - 83 |
| 526 | Osram / Ledvance | Parathom Pro MR16 35 Advanced | 7.0 | HTM70 | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 40 | 1 - 71 |
| 527 | Osram / Ledvance | Parathom Pro MR16 35 Advanced R | 10.0 | HTM70 | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 46 |
| 528 | Osram / Ledvance | Parathom Pro AR111 50 680lm AC12996 | 10.8 | HTM70 | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 46 |
| 529 | Osram / Ledvance | Parathom Pro LEDSpot AR111 50 Adv. | 12.0 | HTM70 | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |
| 530 | Osram / Ledvance | Parathom Classic P25 Advanced | 4.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 28 | 1 - 51 |
| 531 | Osram / Ledvance | Parathom Classic P40 Advanced | 6.0 | Internal | Trailing Edge | 1 - 16 | 1 - 27 | 1 - 30 | 1 - 58 | 1 - 103 |
| 532 | Osram / Ledvance | Parathom DIM R80 100 | 9.6 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 60 |
| 533 | Osram / Ledvance | Parathom PAR16 65 Advanced | 8.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 37 |
| 534 | Osram / Ledvance | Parathom Stick AC21548 | 7.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 535 | Osram / Ledvance | Parathom Stick AC21550 | 7.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 536 | Osram / Ledvance | Parathom Stick AC21554 | 9.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 51 |
| 537 | Osram / Ledvance | Parathom Stick AC21559 | 11.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 538 | Osram / Ledvance | Parathom Stick AC21561 | 11.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 539 | Osram / Ledvance | Parathom Dim PAR16 50 AC27614 | 5.5 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 87 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|------------------|--|-----|----------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 540 | Osram / Ledvance | LED Performance PAR16 50 AC32221 | 5.5 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 541 | Osram / Ledvance | LED Performance PAR16 50 AC32223 | 5.5 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 542 | Osram / Ledvance | LED Performance PAR16 80 AC32242 | 7.5 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 40 | 1 - 72 |
| 543 | Osram / Ledvance | LED Performance PAR16 80 625lm AC10154 | 8.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 55 |
| 544 | Osram / Ledvance | LED Performance PAR16 80 625lm AC10155 | 8.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 55 |
| 545 | Osram / Ledvance | LED Performance PAR16 80 (930) AC20915 | 7.5 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 51 |
| 546 | Osram / Ledvance | LED Performance PAR16 80 (940) | 7.5 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 51 |
| 547 | Osram / Ledvance | LED Performance MR16 50 630lm AC10144 | 7.0 | HTM70 | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 32 | 1 - 57 |
| 548 | Osram / Ledvance | LED Performance Classic A filament AC24263 | 7.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 61 |
| 549 | Osram / Ledvance | LED Performance Classic A60 filament AC08113 | 7.5 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 40 | 1 - 72 |
| 550 | Osram / Ledvance | LED Performance Classic A60 filament AC08117 | 7.5 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 40 | 1 - 72 |
| 551 | Osram / Ledvance | LED Performance Classic A60 AC28043 | 9.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 33 | 1 - 58 |
| 552 | Osram / Ledvance | LED Performance Classic A60 AC14368 | 9.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 553 | Osram / Ledvance | LED Performance Classic B40 Filament AC24282 | 5.0 | Internal | Trailing Edge | 1 - 16 | 1 - 27 | 1 - 30 | 1 - 59 | 1 - 105 |
| 554 | Osram / Ledvance | LED Superstar PAR16 35 (Adv) | 3.6 | Internal | Trailing Edge | 1 - 16 | 1 - 28 | 1 - 31 | 1 - 60 | 1 - 107 |
| 555 | Osram / Ledvance | LED Superstar PAR16 35 Advanced | 4.8 | Internal | Trailing Edge | 1 - 16 | 1 - 27 | 1 - 30 | 1 - 59 | 1 - 105 |
| 556 | Osram / Ledvance | LED Superstar PAR16 35 Advanced | 5.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 88 |
| 557 | Osram / Ledvance | LED Superstar PAR16 50 | 4.6 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 52 | 1 - 93 |
| 558 | Osram / Ledvance | LED Superstar PAR16 50 Advanced | 4.6 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 52 | 1 - 93 |
| 559 | Osram / Ledvance | LED Superstar PAR16 50 (Adv) | 5.0 | Internal | Trailing Edge | 1 - 16 | 1 - 27 | 1 - 30 | 1 - 59 | 1 - 105 |
| 560 | Osram / Ledvance | LED Superstar PAR16 50 Advanced | 5.3 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 44 | 1 - 78 |
| 561 | Osram / Ledvance | LED Superstar PAR16 50 (Adv) | 5.5 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 562 | Osram / Ledvance | LED Superstar PAR16 50 (Adv) | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 563 | Osram / Ledvance | LED Superstar PAR16 50 Advanced | 7.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 41 | 1 - 72 |
| 564 | Osram / Ledvance | LED Superstar PAR16 50 Advanced | 7.5 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 61 |
| 565 | Osram / Ledvance | LED Superstar MR16 50 Advanced | 8.5 | HTM70 | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 33 | 1 - 58 |
| 566 | Osram / Ledvance | LED Superstar MR16 35 Advanced | 4.9 | HTM70 | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 52 | 1 - 93 |
| 567 | Osram / Ledvance | LED Superstar MR16 35 Advanced | 5.0 | HTM70 | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 52 | 1 - 93 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|------------------|-------------------------------------|------|--------------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 568 | Osram / Ledvance | LED Superstar MR16 35 Advanced | 6.8 | HTM70 | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 55 |
| 569 | Osram / Ledvance | LED Superstar MR16 35 Advanced | 6.5 | HTM70 | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 52 | 1 - 93 |
| 570 | Osram / Ledvance | LED Superstar Classic B 25 Advanced | 4.5 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 41 | 1 - 72 |
| 571 | Osram / Ledvance | LED Superstar Classic B 40 | 5.7 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 572 | Osram / Ledvance | LED Superstar Classic B 40 Filament | 4.5 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 573 | Osram / Ledvance | LED Superstar Classic B 40 Advanced | 6.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 574 | Osram / Ledvance | LED Superstar Classic P 25 Advanced | 4.5 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 41 | 1 - 72 |
| 575 | Osram / Ledvance | LED Superstar Classic A 60 | 8.5 | Internal | Trailing Edge | 1 - 7 | 1 - 13 | 1 - 14 | 1 - 28 | 1 - 49 |
| 576 | Osram / Ledvance | LED Superstar Classic A 60 | 9.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 40 | 1 - 72 |
| 577 | Osram / Ledvance | LED Superstar Classic A 60 Filament | 6.5 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 578 | Osram / Ledvance | LED Superstar Classic A 60 Advanced | 10.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 54 |
| 579 | Osram / Ledvance | LED Superstar Classic A 60 Advanced | 12.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 55 |
| 580 | Osram / Ledvance | LED Superstar Globe 95 60 Advanced | 9.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 13 | 1 - 22 |
| 581 | Osram / Ledvance | LED Superstar Globe 75 | 12.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 22 | 1 - 39 |
| 582 | Osram / Ledvance | LEDinestra Advanced | 6.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 583 | Osram / Ledvance | LEDinestra DIM AC18698 | 4.5 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 45 | 1 - 80 |
| 584 | Osram / Ledvance | LEDinestra DIM AC18704 | 7.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 45 | 1 - 79 |
| 585 | Osram / Ledvance | LEDinestra DIM AC18705 | 15.0 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 19 | 1 - 34 |
| 586 | Osram / Ledvance | Vintage 1906 LED Edison (filament) | 7.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 587 | Osram / Ledvance | RDL 2014163 | 5.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 32 | 1 - 58 |
| 588 | Osram / Ledvance | Luxpoint Mini G2 | 12.0 | Internal | Trailing Edge | 2 - 7 | 2 - 12 | 2 - 13 | 2 - 26 | 2 - 46 |
| 589 | Pharox | MR16 5W | 5.0 | Pharox Transformer | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 41 | 1 - 73 |
| 590 | Pharox | P200 P45 | 4.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 591 | Pharox | P200 P45 | 4.0 | Internal | Leading Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 17 | 1 - 30 |
| 592 | Pharox | P200 Candle | 3.5 | Internal | Leading Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 32 |
| 593 | Robus | R50GU10D | 5.0 | Internal | Leading Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 45 |
| 594 | Pharox | GU10 | 5.5 | Internal | Trailing Edge | 1 - 11 | 1 - 18 | 1 - 20 | 1 - 39 | 1 - 70 |
| 595 | Pharox | GU10 | 5.5 | Internal | Leading Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 21 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-----------------|---|------|---------------------|-------------------------------|-------------------------|--------|--------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 596 | Pharox | P300 GU10 | 5.5 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 27 | 1 - 48 |
| 597 | Pharox | P600 | 8.5 | Internal | Trailing Edge | 1 - 5 | 1 - 9 | 1 - 10 | 1 - 20 | 1 - 36 |
| 598 | Pharox | #105010 360lm (Candle) | 4.0 | Internal | Trailing Edge | 1 - 32 | 1 - 55 | 1 - 61 | 1 - 119 | 1 - 210 |
| 599 | Pharox | #105011 320lm (Flame Filament) | 4.0 | Internal | Trailing Edge | 1 - 32 | 1 - 55 | 1 - 61 | 1 - 119 | 1 - 210 |
| 600 | Pharox | #105012 410lm (Candle Filament) | 4.0 | Internal | Trailing Edge | 1 - 32 | 1 - 55 | 1 - 61 | 1 - 119 | 1 - 210 |
| 601 | Pharox | #105510 400lm (Filament) | 4.0 | Internal | Trailing Edge | 1 - 32 | 1 - 55 | 1 - 61 | 1 - 119 | 1 - 210 |
| 602 | Pharox | #106010 360lm (Bulb) | 4.0 | Internal | Trailing Edge | 1 - 27 | 1 - 46 | 1 - 51 | 1 - 99 | 1 - 175 |
| 603 | Pharox | #106011 400lm (Filament) | 4.0 | Internal | Trailing Edge | 1 - 27 | 1 - 46 | 1 - 51 | 1 - 99 | 1 - 175 |
| 604 | Pharox | #106012 320lm (Flame Filament) | 4.0 | Internal | Trailing Edge | 1 - 27 | 1 - 46 | 1 - 51 | 1 - 99 | 1 - 175 |
| 605 | Pharox | #106510 600lm (Filament) | 6.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 606 | Pharox | P800 A60 Lamp 470lm | 7.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 61 |
| 607 | Pharox | P800 A60 Lamp 810lm | 10.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 42 |
| 608 | PioLed Lighting | GU10 | 3.0 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 54 | 1 - 95 |
| 609 | PioLed Lighting | GU10 | 4.5 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 45 | 1 - 79 |
| 610 | PioLed Lighting | GU10 | 5.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 43 | 1 - 76 |
| 611 | PioLed Lighting | GU10 | 6.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 54 |
| 612 | PioLed Lighting | GU10 DD026 Combat | 6.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 613 | PioLed Lighting | GU10 DD027 Combat | 6.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 47 | 1 - 83 |
| 614 | PioLed Lighting | GU10 600lm | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 48 | 1 - 86 |
| 615 | PioLed Lighting | LED Filament Candle | 4.0 | Internal | Trailing Edge | 1 - 23 | 1 - 40 | 1 - 44 | 1 - 86 | 1 - 152 |
| 616 | PioLed Lighting | Vers 3CCT GU10 | 7.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 617 | PioLed Lighting | LED Candle Lite | 4.5 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 65 | 1 - 115 |
| 618 | PioLed Lighting | Punch Dimmable LED downlight | 10.0 | PIO-PS-10W-CC 250mA | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 619 | PioLed Lighting | Punch Dimmable LED downlight | 15.0 | PIO-PS-15W-CC 350mA | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 19 | 1 - 33 |
| 620 | PioLed Lighting | Filament LED Bulb (A60) | 6.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 621 | PioLed Lighting | PIO-CL-6W Iris (2 in 1 ceiling light 3CCT) | 6.0 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 622 | PioLed Lighting | PIO-CL-12W Iris (2 in 1 ceiling light 3CCT) | 12.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 46 |
| 623 | PioLed Lighting | PIO-CL-18W Iris (2 in 1 ceiling light 3CCT) | 18.0 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 32 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-------------------|--|------|----------------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 624 | PioLed Lighting | PIO-CL-6W | 6.0 | PIO-CL-6W (300mA) | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 46 | 1 - 82 |
| 625 | PioLed Lighting | PIO-CL-12W | 12.0 | S-CV-240-PL (300mA) | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 47 |
| 626 | PioLed Lighting | PIO-CL-18W | 18.0 | S-CV-240-PL (300mA) | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 33 |
| 627 | PioLed Lighting | PIO-CL-24W | 24.0 | S-CV-240-PL (300mA) | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 13 | 1 - 23 |
| 628 | PioLed Lighting | LED Ceiling panel | 40.0 | S-48-24 & PS-40W-DIM | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 9 | 1 - 16 |
| 629 | PioLed Lighting | LED Ceiling panel | 65.0 | S-72-24 & PS-60W-DIM | Trailing Edge | 1 - 1 | 1 - 2 | 1 - 2 | 1 - 5 | 1 - 9 |
| 630 | PioLed Lighting | LED Ceiling Light 600x600 | 40.0 | PL-40W & PS-40W-DIM | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 9 | 1 - 16 |
| 631 | PioLed Lighting | LED Ceiling Light 600x1200 | 60.0 | PL-60W & PS-60W-DIM | Trailing Edge | 1 - 1 | 1 - 2 | 1 - 2 | 1 - 5 | 1 - 10 |
| 632 | PioLed Lighting | LED Panel Light | 18.0 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 32 |
| 633 | PioLed Lighting | LED Panel Light 600x600 3CCT | 40.0 | PIO-PS-40W-DIM | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 8 | 1 - 15 |
| 634 | PioLed Lighting | 230VAC LED Tapelight 1m * | 7.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 46 | 1 - 81 |
| 635 | PioLed Lighting | 230VAC LED Tapelight (ver 2) 1m * | 7.0 | PIO-230-STR-P | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 636 | Philips / Signify | Master LEDspot GU10 40D | 4.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 33 | 1 - 58 |
| 637 | Philips / Signify | Master LEDspot GU10 MV Value | 4.3 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 63 | 1 - 112 |
| 638 | Philips / Signify | Master LEDspot GU10 MV Value | 5.3 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 639 | Philips / Signify | Master LEDspot Value GU10 Dimmable | 3.7 | Internal | Trailing Edge | 1 - 21 | 1 - 36 | 1 - 40 | 1 - 78 | 1 - 139 |
| 640 | Philips / Signify | Master LEDspot Value GU10 Dimtone | 3.7 | Internal | Trailing Edge | 1 - 21 | 1 - 36 | 1 - 40 | 1 - 78 | 1 - 139 |
| 641 | Philips / Signify | Master LEDspot Value GU10 Dimmable | 4.9 | Internal | Trailing Edge | 1 - 18 | 1 - 31 | 1 - 34 | 1 - 66 | 1 - 116 |
| 642 | Philips / Signify | Master LEDspot Value GU10 Dimmable 380lm | 4.9 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 643 | Philips / Signify | Master LEDspot Value GU10 Dimtone | 4.9 | Internal | Trailing Edge | 1 - 18 | 1 - 31 | 1 - 34 | 1 - 66 | 1 - 116 |
| 644 | Philips / Signify | Master LEDspot GU10 40D (MV) | 6.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 28 | 1 - 50 |
| 645 | Philips / Signify | Master LEDspot GU10 40D | 7.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 28 | 1 - 50 |
| 646 | Philips / Signify | Master LEDspot GU10 40D | 8.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 13 | 1 - 22 |
| 647 | Philips / Signify | Master LEDspot GU10 PF | 6.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 47 |
| 648 | Philips / Signify | Master LEDcandle E14 | 3.0 | Internal | Trailing Edge | 1 - 15 | 1 - 25 | 1 - 28 | 1 - 54 | 1 - 96 |
| 649 | Philips / Signify | Master LEDcandle E14 Deco Classic | 4.5 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 65 | 1 - 115 |
| 650 | Philips / Signify | Master LEDbulb E27 | 12.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 38 |
| 651 | Philips / Signify | Master LEDspot GU5.3 MR16 | 7.0 | External | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 52 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-------------------|---------------------------------|------|----------------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 652 | Philips / Signify | Master LEDspot GU5.3 MR16 | 10.0 | External | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 25 | 1 - 45 |
| 653 | Philips / Signify | Master LEDspot GU10 MV | 5.4 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 40 | 1 - 72 |
| 654 | Philips / Signify | Master LEDspot GU10 MV Value | 3.5 | Internal | Trailing Edge | 1 - 19 | 1 - 32 | 1 - 36 | 1 - 70 | 1 - 124 |
| 655 | Philips / Signify | Master LEDspot ExpertColor GU10 | 3.9 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 75 | 1 - 133 |
| 656 | Philips / Signify | Master LEDspot Value GU10 | 4.9 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 657 | Philips / Signify | Master LEDspot MV GU10 | 5.0 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 658 | Prime K R | 4" (DL-PRIME-K-4-R15-840-45-SD) | 15.0 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |
| 659 | Prime K R | 6" (DL-PRIME-K-6-R20-840-75-D) | 20.0 | Internal | Trailing Edge | 1 - 5 | 1 - 9 | 1 - 10 | 1 - 20 | 1 - 36 |
| 660 | Prime K R | 8" (DL-PRIME-K-8-R20-840-90-D) | 20.0 | Internal | Trailing Edge | 1 - 5 | 1 - 9 | 1 - 10 | 1 - 20 | 1 - 36 |
| 661 | Prime K R | 8" (DL-PRIME-K-8-R30-840-90-D) | 30.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 10 | 1 - 18 |
| 662 | Province Lighting | GU10 200039 (6938274093234) | 7.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 32 | 1 - 57 |
| 663 | Province Lighting | GU10 200747 (4000K) | 7.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 60 |
| 664 | Province Lighting | GU10 200980 (3000K) | 7.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 60 |
| 665 | Radiant | LED 140 GU10 | 5.0 | Internal | Trailing Edge | 1 - 18 | 1 - 31 | 1 - 34 | 1 - 66 | 1 - 116 |
| 666 | Radiant | LED 121 GU10 | 7.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 667 | Radiant | LED 121 RLL 121 CW GU10 | 5.5 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 46 |
| 668 | Radiant | LED 121/1 RLL 121 DL GU10 | 7.0 | Internal | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 15 | 1 - 26 |
| 669 | Radiant | LED 122 GU10 | 7.0 | Internal | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 15 | 1 - 26 |
| 670 | Radiant | LED 112 GU10 | 7.0 | Internal | Trailing Edge | 1 - 2 | 1 - 3 | 1 - 3 | 1 - 7 | 1 - 12 |
| 671 | Radiant | LED 025 | 25.0 | Radiant 700mA driver | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 8 | 1 - 13 |
| 672 | Radiant | LED 032 | 32.0 | Radiant D700040NT | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 10 | 1 - 18 |
| 673 | Radiant | LED076 GU10 6.5W | 6.5 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 674 | Radiant | GU10 6.5W | 6.5 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 18 | 1 - 33 |
| 675 | Radiant | GU10 | 5.0 | Internal | Trailing Edge | 1 - 16 | 1 - 28 | 1 - 31 | 1 - 60 | 1 - 107 |
| 676 | Radiant | GU10 8W Sharp | 8.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 45 | 1 - 80 |
| 677 | Radiant | 5.4W Downlighter LDL001 | 5.4 | Radiant 350mA driver | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 45 | 1 - 81 |
| 678 | Radiant | 9.7W Downlighter LDL002 | 9.7 | Radiant 350mA driver | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 679 | Radiant | 23W Downlighter LDL025 | 23.0 | Radiant 700mA driver | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 8 | 1 - 13 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-------------------|--------------------------------|------|-----------------------|-------------------------------|-------------------------|---------|---------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 680 | Radiant | 23W Downlighter LDL009 | 23.0 | Radiant 700mA driver | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 4 | 1 - 8 | 1 - 13 |
| 681 | Radium | RaLED PAR16 50 (431 19056) | 4.6 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 52 | 1 - 93 |
| 682 | Radium | RL-A60 DIM | 10.0 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 19 | 1 - 34 |
| 683 | Regent Lighting | Perox RS10W- 500mA | 10.0 | Lumotech Minidim 12VA | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 47 |
| 684 | Regent Lighting | Kibo 70 (K70R) | 13.0 | Tridonic LCA 21W | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 37 |
| 685 | Regent Lighting | Module 25W | 25.0 | Tridonic LCBI 25W | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 15 | 1 - 26 |
| 686 | Renesola | GU10 (RG10D006AY03) | 6.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 25 | 1 - 44 |
| 687 | Renesola | Candle (RCD007AE01) | 6.5 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 688 | Renesola | Bulb A60 (RA60D009AE01) | 9.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 689 | Robus | RTA9P230 | 9.2 | Internal | Trailing Edge | 1 - 21 | 1 - 36 | 1 - 40 | 1 - 77 | 1 - 136 |
| 690 | Robus | 9WDLCCCT3 | 9.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 35 | 1 - 62 |
| 691 | Robus | RF7LEDDWW | 9.0 | Robus R10LED200DB | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 53 |
| 692 | Robus | Taylor 3CCT | 9.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 61 |
| 693 | SAA | SP77 GU10 | 8.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 694 | SAA | SP91 GU10 | 6.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 45 | 1 - 80 |
| 695 | SAA | SP95 GU10 | 9.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 11 | 1 - 19 |
| 696 | Samsung | SI-M8V073BD1EU PAR16 | 6.7 | Internal | Trailing Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 17 | 1 - 29 |
| 697 | Samsung | SI-M8W0773BD1EU PAR16 | 6.7 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 37 |
| 698 | Samsung | SI-M8V093BD1EU PAR16 | 7.7 | Internal | Trailing Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 16 | 1 - 28 |
| 699 | Seoul Semi | Acrich AC3-2 | 5.0 | COB | Trailing Edge | 1 - 21 | 1 - 36 | 1 - 40 | 1 - 77 | 1 - 136 |
| 700 | Schiefer Lighting | LF023841502 E14 Filament 140lm | 1.5 | Internal | Trailing Edge | 1 - 75 | 1 - 130 | 1 - 144 | 1 - 277 | 1 - 492 |
| 701 | Schiefer Lighting | LF023840302 E14 Filament 320lm | 4.0 | Internal | Trailing Edge | 1 - 26 | 1 - 45 | 1 - 50 | 1 - 96 | 1 - 170 |
| 702 | Schiefer Lighting | LF023830302 E14 Filament 320lm | 4.0 | Internal | Trailing Edge | 1 - 26 | 1 - 45 | 1 - 50 | 1 - 96 | 1 - 170 |
| 703 | Schiefer Lighting | LF023821502 E27 Filament 150lm | 1.5 | Internal | Trailing Edge | 1 - 75 | 1 - 130 | 1 - 144 | 1 - 277 | 1 - 492 |
| 704 | Schiefer Lighting | L023871302 E27 Filament 320lm | 4.0 | Internal | Trailing Edge | 1 - 26 | 1 - 45 | 1 - 50 | 1 - 96 | 1 - 170 |
| 705 | Schiefer Lighting | LF023870509 E27 Filament 140lm | 5.5 | Internal | Trailing Edge | 1 - 18 | 1 - 31 | 1 - 34 | 1 - 65 | 1 - 116 |
| 706 | Schiefer Lighting | L023810302 E27 Filament 320lm | 4.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 159 |
| 707 | Schiefer Lighting | LF023880302 E27 Filament 320lm | 4.0 | Internal | Trailing Edge | 1 - 24 | 1 - 41 | 1 - 46 | 1 - 90 | 1 - 159 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|---------------------|---|------|----------------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 708 | Smartglo | GU10-6W | 6.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 46 | 1 - 81 |
| 709 | Spazio Lighting | GU10 (LA 410540180902) | 5.0 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 5 | 1 - 10 | 1 - 18 |
| 710 | Spazio Lighting | GU10 (LA 4205903640) | 5.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 45 |
| 711 | Spazio Lighting | GU10 (LA 4207983627) 2700K | 7.5 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 712 | Spazio Lighting | GU10 (LA 4207983640) 4000K | 7.5 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 713 | Spazio Lighting | GU10 LED BULB | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 37 |
| 714 | Spazio Lighting | GU10 410/40100702 | 7.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 39 | 1 - 69 |
| 715 | Spazio Lighting | GU10 LA 410730200702 | 7.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 46 | 1 - 81 |
| 716 | Spazio Lighting | GU10 (LA 42059027) SMD CRI80 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 717 | Spazio Lighting | GU10 (LA 410530191102) SMD CRI80 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 718 | Spazio Lighting | GU10 (LA 410540191102) SMD CRI80 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 719 | Spazio Lighting | GU10 (LA 410560191102) SMD CRI80 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 720 | Spazio Lighting | GU10 (LA 42059040) SMD CRI90 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 721 | Spazio Lighting | GU10 (LA 4205903627) 2700K CRI90 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 722 | Spazio Lighting | GU10 (LA 4205903630) 3000K CRI90 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 723 | Spazio Lighting | GU10 (LA 4205903640) 4000K CRI90 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 724 | Spazio Lighting | GU10 (LA 42059065) | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 725 | Spazio Lighting | GU10 (LA 42059032) SMD CRI90 | 5.5 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 54 | 1 - 95 |
| 726 | Spazio Lighting | GU10 (LA 41058030) | 5.5 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 43 | 1 - 76 |
| 727 | Spazio Lighting | G95 LED filament lamp | 4.0 | Internal | Trailing Edge | 1 - 17 | 1 - 30 | 1 - 33 | 1 - 64 | 1 - 114 |
| 728 | Spazio Lighting | Candle filament lamp (LA 4303504ES2701) | 4.0 | Internal | Trailing Edge | 1 - 27 | 1 - 46 | 1 - 51 | 1 - 99 | 1 - 175 |
| 729 | Spazio Lighting | TCI LD0091A (900mA x 4) | 31.0 | Tridonic LCBI 25W | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 21 |
| 730 | Spazio Lighting | LED Panel lamp PR225A | 18.0 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 19 | 1 - 34 |
| 731 | Spazio Lighting | 2478 Round Tilt D/L | 15.0 | Spazio 7317.350.18.D | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |
| 732 | Sunlit Technologies | LED GU10 (#20436) Cool White | 5.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 54 |
| 733 | Sunlit Technologies | LED GU10 (#20429) Warm White | 5.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 54 |
| 734 | Sunlit Technologies | LED GU10 | 7.0 | Internal | Trailing Edge | 1 - 16 | 1 - 27 | 1 - 30 | 1 - 59 | 1 - 105 |
| 735 | Sunlit Technologies | LED A60 (#20207) Cool White | 10.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 25 | 1 - 45 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|---------------------|----------------------------------|------|----------|-------------------------------|-------------------------|--------|--------|---------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 736 | Sunlit Technologies | LED A60 (#20214) Warm White | 10.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 25 | 1 - 45 |
| 737 | Sunseon | T5 Dimmable LED Tube 1150mm | 21.0 | Sunseon | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 54 |
| 738 | Sylvania | Candle LED C35 (161998020901) | 5.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 48 | 1 - 86 |
| 739 | Sylvania | GU10 RefLED ES50 dim | 5.5 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 90 |
| 740 | Sylvania | RefLED MR16 Eco (non dimmable) | 6.5 | External | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 37 |
| 741 | Sylvania | RefLED+ ES50 | 6.8 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 22 | 1 - 39 |
| 742 | Sylvania | RefLED+ ES50 V2 | 5.5 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 53 |
| 743 | Sylvania | RefLED Superia ES50 V2.1 | 6.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 53 |
| 744 | Sylvania | RefLED+ ES50 GU10 Dim 830 | 5.5 | Internal | Trailing Edge | 1 - 11 | 1 - 18 | 1 - 20 | 1 - 39 | 1 - 70 |
| 745 | Sylvania | RefLED+ ES50 GU10 Dim 830 40d SL | 6.5 | Internal | Trailing Edge | 1 - 4 | 1 - 6 | 1 - 7 | 1 - 15 | 1 - 27 |
| 746 | Sylvania | RefLED ES50 | 5.5 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 90 |
| 747 | Sylvania | RefLED ES50 DIM 460lm (6288) | 6.3 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 43 | 1 - 76 |
| 748 | Sylvania | ToLED0 Retro Candle (0028446) | 4.5 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 44 | 1 - 78 |
| 749 | Sylvania | RefLED ES50 Hi-Spot GU10 | 6.5 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 52 | 1 - 92 |
| 750 | Synerji | GU10 | 5.0 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 42 |
| 751 | Synerji | GU10 (0517) | 5.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 41 | 1 - 73 |
| 752 | Synerji | GU10 (0517) | 6.5 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 52 |
| 753 | Synerji | GU10 (0916) | 6.5 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 23 | 1 - 41 |
| 754 | Synerji | GU10 (0418, 0719) | 6.5 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 65 |
| 755 | Synerji | GU10 | 7.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 21 | 1 - 38 |
| 756 | Synerji | Candle (1215) | 5.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 45 |
| 757 | Synerji | Candle (0918) | 5.5 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 48 | 1 - 85 |
| 758 | Synerji | Candle (0719) | 5.5 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 40 | 1 - 72 |
| 759 | Synerji | GLS Lamp E27 (0719) | 10.0 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |
| 760 | Synerji | Deco Filament A60 | 3.0 | Internal | Trailing Edge | 1 - 27 | 1 - 47 | 1 - 52 | 1 - 102 | 1 - 180 |
| 761 | Synerji | Deco Filament BT215 | 4.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 74 | 1 - 132 |
| 762 | Synerji | Deco Filament ST64 | 4.0 | Internal | Trailing Edge | 1 - 20 | 1 - 34 | 1 - 38 | 1 - 74 | 1 - 132 |
| 763 | Synerji | SYFD006AMES (Deco Filament A60) | 3.0 | Internal | Trailing Edge | 1 - 26 | 1 - 45 | 1 - 50 | 1 - 97 | 1 - 172 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|------------------|--------------------------------------|------|---------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 764 | Synerji | SYFD008AMES (Deco Filament G125) | 4.0 | Internal | Trailing Edge | 1 - 19 | 1 - 33 | 1 - 37 | 1 - 72 | 1 - 127 |
| 765 | Synerji | SYLGL11WWBC (GLS A60) | 11.0 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |
| 766 | Synerji | SYLGL11WWES (GLS A60) | 11.0 | Internal | Trailing Edge | 1 - 6 | 1 - 11 | 1 - 12 | 1 - 24 | 1 - 43 |
| 767 | Synerji | SYLC5.5WWE14 (Candle lamp) | 5.5 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 53 | 1 - 95 |
| 768 | Swiss LED | GU10 SWISLGU55ED65 | 5.5 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 27 | 1 - 48 |
| 769 | Swiss LED | GU10 E390SGNCA | 5.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 25 | 1 - 44 |
| 770 | Swiss LED | Bulb S2E0210D | 10.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 35 | 1 - 63 |
| 771 | The Light Bar | L004 GU10 3000k | 5.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 43 | 1 - 76 |
| 772 | The Light Bar | L005 GU10 4000k | 5.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 43 | 1 - 76 |
| 773 | Tridonic | Engine SLA AC G2 50mm SNC (28002834) | 9.5 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 52 |
| 774 | Venture Lighting | VLED DOM026 | 6.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 775 | Venture Lighting | SPL071 | 5.0 | Internal | Trailing Edge | 1 - 12 | 1 - 20 | 1 - 22 | 1 - 43 | 1 - 76 |
| 776 | Venture Lighting | SPL073 | 9.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 34 | 1 - 60 |
| 777 | Venture Lighting | SPL070 | 12.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 25 | 1 - 44 |
| 778 | Verbatim | #52017 PAR38 (E27) | 18.0 | Internal | Trailing Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 16 | 1 - 29 |
| 779 | Verbatim | #52019 Classic A E27 | 9.0 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 35 | 1 - 62 |
| 780 | Verbatim | #52028 MR16 | 7.0 | Verbatim LW70 | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 781 | Verbatim | #52034 E27 | 20.0 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 19 | 1 - 33 |
| 782 | Verbatim | #52040 GU10 | 6.0 | Internal | Trailing Edge | 1 - 14 | 1 - 23 | 1 - 26 | 1 - 51 | 1 - 91 |
| 783 | Verbatim | #52041 GU10 | 8.5 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 784 | Verbatim | #52045 GU10 | 6.5 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 50 | 1 - 89 |
| 785 | Verbatim | #52047 Classic B E14 | 3.7 | Internal | Trailing Edge | 1 - 17 | 1 - 29 | 1 - 32 | 1 - 62 | 1 - 111 |
| 786 | Verbatim | #52049 GU10 | 7.0 | Internal | Trailing Edge | 1 - 16 | 1 - 28 | 1 - 31 | 1 - 60 | 1 - 106 |
| 787 | Verbatim | #52200 GU10 | 7.0 | Internal | Trailing Edge | 1 - 12 | 1 - 21 | 1 - 23 | 1 - 47 | 1 - 83 |
| 788 | Verbatim | #52205 AR111 G53 | 15.0 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 19 | 1 - 33 |
| 789 | Verbatim | #52206 MR16 | 7.0 | Verbatim LW70 | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 53 |
| 790 | Verbatim | #52207 MR16 | 7.0 | Verbatim LW70 | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 791 | Verbatim | #52208 MR16 | 7.0 | Verbatim LW70 | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 53 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-----------------|-----------------------------|------|-----------------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 792 | Verbatim | #52209 MR16 | 7.0 | Verbatim LW70 | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 793 | Verbatim | #52210 MR16 | 7.0 | Verbatim LW70 | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 35 | 1 - 62 |
| 794 | Verbatim | #52211 MR16 | 7.0 | Verbatim LW70 | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 795 | Verbatim | #52212 MR16 | 3.5 | Verbatim LW70 | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 796 | Verbatim | #52214 GU10 | 7.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 50 | 1 - 89 |
| 797 | Verbatim | #52217 GU10 | 7.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 42 | 1 - 74 |
| 798 | Verbatim | #52220 Classic A E27 | 7.5 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 65 |
| 799 | Verbatim | #52224 MR16 | 6.5 | Verbatim LW70 | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 30 | 1 - 53 |
| 800 | Verbatim | #52225 E27 | 7.7 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 36 | 1 - 64 |
| 801 | Verbatim | #52230 MR16 | 7.0 | Verbatim LW70 | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 802 | Verbatim | #52231 MR16 | 7.0 | Verbatim LW70 | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 66 |
| 803 | Verbatim | #52235 GU10 | 7.3 | Internal | Trailing Edge | 1 - 16 | 1 - 28 | 1 - 31 | 1 - 60 | 1 - 106 |
| 804 | Verbatim | #52310 GU10 | 8.5 | Internal | Trailing Edge | 1 - 9 | 1 - 15 | 1 - 17 | 1 - 35 | 1 - 62 |
| 805 | Verbatim | #52308 GU10 | 6.0 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 27 | 1 - 47 |
| 806 | Verbatim | #52322 E27 Globe | 8.8 | Internal | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 26 | 1 - 46 |
| 807 | Verbatim | #52336 E27 Globe | 9.5 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 16 | 1 - 32 | 1 - 56 |
| 808 | Verbatim | #52611 G95 Large Globe | 10.0 | Internal | Trailing Edge | 1 - 6 | 1 - 10 | 1 - 11 | 1 - 22 | 1 - 39 |
| 809 | Verbatim | #52350 GU10 | 8.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 39 | 1 - 69 |
| 810 | Verbatim | #52351 GU10 | 8.0 | Internal | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 39 | 1 - 69 |
| 811 | Verbatim | #52343 AR111 | 10.0 | Verbatim #52900 (70W) | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 25 | 1 - 44 |
| 812 | Verbatim | #64656 GU10 | 8.5 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 31 | 1 - 55 |
| 813 | Verbatim | #65110 GU10 | 6.5 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 49 | 1 - 87 |
| 814 | Verbatim | #65421 GU10 Warm-dim | 7.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 50 | 1 - 89 |
| 815 | Verbatim | AR111 ("non-dimmable") | 14.5 | Internal | Trailing Edge | 1 - 3 | 1 - 5 | 1 - 6 | 1 - 12 | 1 - 22 |
| 816 | Visionary | Iris 2 19W-Dx4K Downlighter | 7.8 | Phoenix P-220MA-D VF | Trailing Edge | 1 - 7 | 1 - 12 | 1 - 13 | 1 - 27 | 1 - 48 |
| 817 | Vossloh-Schwabe | GU10 #556799 | 6.0 | Internal | Trailing Edge | 1 - 5 | 1 - 8 | 1 - 9 | 1 - 19 | 1 - 34 |
| 818 | Vossloh-Schwabe | GU10 #553220 | 7.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 50 | 1 - 89 |
| 819 | Vossloh-Schwabe | GU10 #553221 | 7.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 50 | 1 - 89 |

Shuttle Phase Cut Universal Dimmers (Live In and Load Out, No Neutral required)

Bell-Press dimmer models: 125W, 250W, 500W & 800W. Rotary dimmer models: 225W, 500W & 800W

| NO | LAMP BRAND | MODEL | W | DRIVER | DIMMING MODE (recommended) | MAXIMUM NUMBER OF LAMPS | | | | |
|-----|-----------------|----------------------------------|--------|---------------------|-------------------------------|-------------------------|--------|--------|--------|---------|
| | | | | | | 125W | 225W | 250W | 500W | 800W |
| 820 | Vossloh-Schwabe | GU10 #541126 | 7.0 | Internal | Trailing Edge | 1 - 13 | 1 - 23 | 1 - 25 | 1 - 50 | 1 - 89 |
| 821 | Vossloh-Schwabe | LED COB Module #559774 | 10.0 | Internal | Trailing Edge | 1 - 11 | 1 - 19 | 1 - 21 | 1 - 41 | 1 - 73 |
| 822 | Vossloh-Schwabe | LED COB Module #559779 | 15.0 | Internal | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 52 |
| 823 | Vossloh-Schwabe | LED COB Module #559784 | 20.0 | Internal | Trailing Edge | 1 - 5 | 1 - 9 | 1 - 10 | 1 - 21 | 1 - 36 |
| 824 | Vossloh-Schwabe | Pro Series #550880 | 12.0 | External Integrated | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 51 |
| 825 | Vossloh-Schwabe | Pro Series #550882 | 12.0 | External Integrated | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 51 |
| 826 | Vossloh-Schwabe | Pro Series #550884 | 12.0 | External Integrated | Trailing Edge | 1 - 8 | 1 - 14 | 1 - 15 | 1 - 29 | 1 - 51 |
| 827 | Vossloh-Schwabe | Pro Series #550885 | 18.0 | External Integrated | Trailing Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 17 | 1 - 30 |
| 828 | Vossloh-Schwabe | Pro Series #550886 | 18.0 | External Integrated | Trailing Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 17 | 1 - 30 |
| 829 | Vossloh-Schwabe | Pro Series #550887 | 18.0 | External Integrated | Trailing Edge | 1 - 4 | 1 - 7 | 1 - 8 | 1 - 17 | 1 - 30 |
| 830 | Waco | GU10 Spotlight 6500K J0079480 | 7.0 | External Integrated | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 65 |
| 831 | Waco | GU10 Spotlight 4000K J0079481 | 7.0 | External Integrated | Trailing Edge | 1 - 10 | 1 - 17 | 1 - 19 | 1 - 37 | 1 - 65 |
| 832 | Uniontech SA | GU10 | 5.0 | Internal | Trailing Edge | 1 - 14 | 1 - 24 | 1 - 27 | 1 - 52 | 1 - 92 |
| 833 | Zebbies | GU10 (#3799) | 5.3 | Internal | Trailing Edge | 1 - 13 | 1 - 22 | 1 - 24 | 1 - 47 | 1 - 83 |
| 834 | Generic | 230VAC LED Striplight 60 LED/m * | 8.25/m | Rectified Mains | Trailing Edge | 1 - 16 | 1 - 28 | 1 - 31 | 1 - 60 | 1 - 107 |
| 835 | Generic | Halogen 230VAC GU10 | 50.0 | NA | Trailing Edge | 1 - 2 | 1 - 4 | 1 - 5 | 1 - 10 | 1 - 16 |
| 836 | Generic | Incandescent 230VAC Globe | 60.0 | NA | Trailing Edge | 1 - 2 | 1 - 3 | 1 - 4 | 1 - 8 | 1 - 13 |
| 837 | Generic | Incandescent 230VAC Globe | 100.0 | NA | Trailing Edge | 1 - 1 | 1 - 2 | 1 - 2 | 1 - 5 | 1 - 8 |

NOTES

- 1 All Shuttle universal dimmers are factory default in trailing edge mode since trailing edge dimming is recommended for most dimmable LED's and drivers
- 2 In cases of a specific LED being listed for leading and trailing edge, the leading edge data was requested by the supplier
- 3 If the LED or dimmer supplier does not provide measured data, calculate the maximum number of LED's per dimmer as follows:

$$\text{Max. number of LED's per dimmer} = \frac{\text{Dimmer Max. rating (W/VA)}}{\text{LED's equivalent GLS/Halogen wattage}}$$

- 4 All measurements are conducted at 230VAC 50Hz
- 5 All low voltage lamp loads INCLUDE electronic transformer or driver losses.
- 3 Flicker at low light intensity is sometimes unavoidable – please set the dimmer minimum dim to avoid flicker (refer to relevant dimmer data sheet)
- 4 Some LED's dim to a completely off state – please set the dimmer minimum level to avoid this condition (refer to relevant dimmer data sheet)
- 5 Some Low voltage lamps and transformer combinations might exhibit flicker at various light intensities or might not turn on – please set the dimmer in “MR16 compatibility mode”
- 6 Maximum Load applies only when:
 - A - Supply voltage does not exceed 230VAC
 - B - Dimmer is well ventilated (ambient temperature around the dimmer is below 35°C)
 - C - Only one dimmer per wallbox (please refer to the data sheets for derating factors for multiple dimmers per wallbox)

* LED stays slightly on when dimmer is off – please use a capacitive dummy load as per Shuttle recommendation to avoid this condition

** Lamps may flicker or “pulse” at low to medium intensities – unavoidable lamp characteristic but might be alleviated if the dimmer's minimum is set to above this

Shuttle Lighting Control Systems (Pty) Ltd - Lamp/driver dimmer compatibility testing Disclaimer

Compatibility tests are conducted by Shuttle as guidance, without responsibility for the performance of the lamps and drivers.

The results shown are based on measurements in our test laboratory. Field results may differ from test results depending on conditions at the application site.

Results may vary due to variability in component choices and manufacturing processes by lamp and driver manufacturers.

Please refer to the lamp and driver manufacturers website for specifications, installation and operating instructions